Lawrence Berkeley National Laboratory

Recent Work

Title

PERIOD THREE GENERATION ON MICROWAVE-INDUCED CONSTANT-VOLTAGE STEPS OF JOSEPHSON TUNNEL JUNCTIONS

Permalink

<https://escholarship.org/uc/item/1957t95z>

Author

Mygind, J.

Publication Date

1986-10-01

c.2

Lawrence Berkeley Laboratory

UNIVERSITY OF CALIFORNIA

RECEIVED
LAWRENCE
BERKELEY LABORATORY

DEC 23 1986

LIBRARY AND
DOCUMENTS SECTION

Materials & Molecular Research Division

Presented at the 1986 Applied
Superconductivity Conference, Baltimore, MD,
September 28-October 3, 1986

PERIOD THREE GENERATION ON MICROWAVE-INDUCED
CONSTANT-VOLTAGE STEPS OF
JOSEPHSON TUNNEL JUNCTIONS

J. Mygind, J. Bindslev Hansen, J. Clarke,
G.A. Ovsyannikov, and H. Svensmark

October 1986

TWO-WEEK LOAN COPY

*This is a Library Circulating Copy
which may be borrowed for two weeks*

LBL-22431

c.2

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

PERIOD THREE GENERATION ON MICROWAVE-INDUCED CONSTANT-VOLTAGE STEPS OF JOSEPHSON TUNNEL JUNCTIONS

J. Mygind, J. Bindslev Hansen, J. Clarke,* G. A. Ovsyannikov,** and H. Svensmark
MIDIT (Modellering, Ikke-Lineær Dynamik og Irreversibel Termodynamik)
Physics Laboratory I, The Technical University of Denmark
DK-2800 Lyngby, Denmark

Abstract

We report the observation of one-third harmonic generation in small Josephson tunnel junctions driven with a microwave signal in the frequency range 8 to 18 GHz. This phenomenon was observed both with the junction biased in the zero voltage state and on microwave-induced constant-voltage steps in the current-voltage characteristic. With high levels of applied microwave power the period-tripled signal was detected on steps up to order 120.

Introduction

Over the past six years, there have been extensive digital and analog computer simulations of subharmonic generation and chaotic behavior in microwave-driven Josephson tunnel junctions.¹ Most of these simulations were for zero average voltage. Although there have been relatively few experimental investigations² of these phenomena, we recently reported³ the experimental observation of one-third harmonic generation at zero voltage and current; the results were in reasonable agreement with computer simulations. In this paper we summarize these findings, and present new results for period-tripling in junctions biased on microwave-induced steps at nonzero voltages.

Theoretical Model

According to the resistively shunted junction model (insert Fig. 2) the equation of motion for the phase difference ϕ across a junction biased with both static and microwave currents is

$$\frac{MC}{2e} \frac{d^2\phi}{dt^2} + \frac{M}{2eR} \frac{d\phi}{dt} + I_0 \sin\phi = I + I_m \sin\omega_m t + I_n(t). \quad (1)$$

Here, I_0 is the critical current of the junction, C is the shunt capacitance, R is the shunt resistance, and I , I_m and I_n are the static bias current, the microwave current at frequency ω_m , and the noise current, respectively. This equation contains no spatial dependence of ϕ and therefore models a Josephson junction with dimensions smaller than the Josephson penetration depth. In normalized form Eq. (1) may be written as

$$d^2\phi/d\tau^2 + \alpha_0 d\phi/d\tau + \sin\phi = \rho + \rho_m \sin\Omega\tau + \rho_n(\tau). \quad (2)$$

Here, $\tau = \omega_{po} t$ is the time normalized to the inverse of the maximum plasma frequency, $\omega_{po} = (2eI_0/Mc)^{1/2}$, $\alpha_0 = 1/Q_0 = 1/\omega_{po}RC$ is the damping parameter, $\Omega = \omega_m/\omega_{po}$ is the normalized microwave frequency and ρ , ρ_m and ρ_n are the static bias current, microwave current and noise current normalized to I_0 .

*Permanent address: Department of Physics and Materials and Molecular Research Division, Lawrence Berkeley Laboratory, University of California, Berkeley, California 94720 USA.

**Permanent address: Institute of Radio Engineering and Electronics of the Academy of Sciences of the USSR, Moscow, USSR.

Figure 1. Maximum plasma frequency $\omega_{po}(B)/2\pi$ measured in half-harmonic excitation experiments with applied B-field versus the square root of the suppressed critical current for $0 < B < 4.0$ gauss. Also plotted is $\omega_{po}(0)$ found similarly in the temperature range $3.0 K \leq T \leq 4.8 K$ versus $\sqrt{I_0(0, T)}$. (Junction S-3008)

Equation (2) also models a periodically driven damped pendulum. For zero current bias and in the zero voltage state computer simulations based on this equation show the existence of bands of even- and odd-subharmonic solutions in the microwave frequency-amplitude plane, often separated by regions of chaos.⁴

Experimental Results

We made measurements on 4 underdamped Nb-NbO_x-Pb overlap Josephson tunnel junctions approximately $30 \times 30 \mu m^2$ in area and with a critical current density in the range 10 to 70 A cm⁻². The corresponding Josephson penetration depth varied from about 100 μm to 35 μm . Thus, we could neglect any spatial dependence of ϕ in junctions with the lower critical currents but not necessarily in those with the higher values. The experimental apparatus and measurement techniques were identical to those reported earlier,³ and included detailed *in situ* measurements of the parameters I_0 , ρ_n , ω_{po} (i.e. C), Q_0 (i.e. R) and ρ_m . We could also adjust the maximum plasma frequency ω_{po} by applying a magnetic field B in the plane of the

junction to reduce the critical current $I_0(B, T)$ at a given temperature T . The plasma frequency was measured using half-harmonic excitation,⁵ and is plotted vs. $I_0^{1/2}(B, T)$ in Fig. 1. For this junction, the data yield a value of $C = 80$ pF from the prediction $\omega_{po} = [2eI_0(B, T)/MC]^{1/2}$.

We observed one-third harmonic generation for three different cases:

- (1) For $B = 0$, $\rho = 0$ and $V = 0$, that is, for the junction biased in the zero voltage state. Both narrow-band signals (see Fig. 2) and relatively broad-band noisy (intermittent) signals were observed. In this regime the phase ϕ oscillates about zero with $\langle \dot{\phi} \rangle = 0$.

Figure 2. Typical spectrum analyzer display showing the one-third harmonic generation in a Josephson junction (S-6/7-4) biased in the zero voltage state. For comparison of the linewidths the stored display of the microwave pump signal at 12.426 GHz and the one-third harmonic signal emitted by the junction are shown on the same frequency span. The resolution bandwidth is 100 Hz and the experimental parameters are: $I_0 = 163$ μ A, $\omega_{po}/2\pi = 14.45$ GHz ($\Omega = 0.86$), and $\rho_m = 1.28$. The insert shows the resistively shunted junction model.

- (2) For $B = 0$, $\rho = 0$ and $V = (1/3)M\omega_m/2e$, that is, with the junction biased on the microwave-induced subharmonic step. An example is illustrated in Fig. 3. In this regime ϕ advances with time.
- (3) For $B = 0$, $\rho = 0$ and $V = nM\omega_m/2e$, where n is an integer, that is, when the junction is biased on an integer-valued microwave-induced step. Typical results are shown in Fig. 4. This generation was observed at 13.28 GHz for values of n up to 120, corresponding to a voltage of about 3.3 mV. This voltage was slightly above $(\Delta_{Nb} + \Delta_{Pb})/e = 2.8$ mV, where Δ_{Nb} and Δ_{Pb} are the measured energy gaps of niobium and lead. In this regime, ϕ advances with time. These results were obtained only in the junction (S-5001) with the higher critical current (585 μ A), for which there may have been a significant spatial nonuniformity of the phase difference, and in the presence of a magnetic field. The amplitude of the 1/3 harmonic signal was very sensitive to the values of B , ρ_m , and ρ . With $B = 4$ gauss, $\omega_{po}/2\pi = 23.2$ GHz, $\alpha = 0.05$ and $T_{bath} = 4.2$ K, two representative points at which we observed 1/3 harmonic generation were $(\Omega, \rho_m) = (2.1, 100)$ and $(2.3, 82)$. The fact that one can observe period 3 generation on integer-valued microwave induced steps appears not to have been predicted in any simulation for a spatially

uniform phase difference and $B = 0$.

The state diagram plotted in Fig. 5 summarizes the results of our experiments and digital simulations for one-third harmonic generation at $V = 0$. In studying the experimental results, one should bear in mind that the 1/3 harmonic signal could be observed only at

Figure 3. Amplitude of the detected one-third harmonic signal (upper trace) and static voltage (lower trace) as functions of the current bias at two different levels of pump power. (a) XY recording with one-third harmonic in the zero voltage state. (b) XY recording for a weak one-third harmonic signal on one-third harmonic steps (barely visible in the I-V characteristic).

discrete frequencies for which there was good coupling between the junction and the detector. Thus, the discrete points almost certainly represent a broad region over which the subharmonic generation occurs. In the same way, the simulations represent a continuous range of drive frequency and amplitude over which one-third harmonic signal is generated. Given the uncertainties in the determination of the experimental parameters, particularly the magnitude of the microwave current, the agreement between the experimental and simulated values is quite reasonable.

We are continuing these experiments to search for higher order subharmonics and to study routes to chaos. We are also carrying out computer simulations in order to understand the one-third harmonic generation on the microwave-induced steps.

Acknowledgments

We are indebted to S. Hjorth, I. Rasmussen, and J. L. Skov for the sample fabrication. We gratefully acknowledge discussions with N. F. Pedersen, M. Levinsen, M. R. Samuelsen, G. F. Eriksen, D. Welner, and C. A. D. Winther. Two of us (JC and GAO) would like to thank the members of Physics Laboratory I for their hospitality during the course of this work. This work was supported in part by the Danish Natural Science Research Council, by the Danish Ministry of Education (Program of Cultural Exchange between Denmark and the USSR), and by the Director, Office of

Figure 4. Typical XY recording of the bias current dependence of the voltage (upper trace) and the corresponding detected one-third harmonic power (lower trace) generated on (a) even and (b) odd numbered microwave-induced steps for junction S-5001 at 4.2 K. The detected frequency was 6.122 GHz, the resolution bandwidth was 10 kHz, the microwave frequency $\omega_m/2\pi$ was 18.366 GHz, and the plasma frequency $\omega_{po}(0)/2\pi$ was 23.2 GHz. The plasma frequency was tuned by means of a magnetic field (see text) to produce reduced microwave frequencies of (a) $\Omega = 2.3$ and (b) $\Omega = 2.1$.

Energy Research, Office of Basic Energy Sciences, Materials Sciences Division of the U.S. Department of Energy under Contract No. DE-AC03-76SF00098.

Figure 5. Normalized microwave pump amplitude ρ_m vs. normalized pump frequency Ω showing regions for which one-third harmonic signal occurs. The results of numerical simulations are also shown.

Experiment. Junction S-6/7-4 with $B = 0$: ■ narrow band 1/3-harmonic and □ broadband noisy or intermittent 1/3-harmonic at $V = 0$, $\rho = 0$ (case 1); △ 1/3-harmonic at $V = (1/3)\hbar\omega_m/2e$ (case 2). Parameters: $I_0 = 163 \mu A$, $\omega_{po}/2\pi = 14.45$ GHz, $\alpha = 0.05$ and $T_{bath} = 4.2$ K.

Simulations. • narrow band 1/3-harmonic at $V = 0$, $\alpha = 0.05$.

References

1. For a comprehensive list of references see: R. L. Kautz, "Chaotic States of rf-Biased Josephson Junctions", J. Appl. Phys. 52, 6241-6246, 1981; "Chaos and Thermal Noise in the rf-Biased Josephson Junction", *ibid* 58, 424-440, 1985; R. L. Kautz and R. Monaco, "Survey of Chaos in the rf-Biased Josephson Junction", *ibid* 57, 875-889, 1985.
2. For a review of the experiments, see J. Kurkijärvi, "Chaos in Junctions and Devices", pp. 377-407 in Superconducting Quantum Interference Devices and their Applications, Eds. H. D. Hahlbohm and H. Lübbig, Walter de Gruyter, Berlin, 1985.
3. J. Bindslev Hansen, J. Clarke, J. Mygind, G. A. Ovsyannikov, and H. Svensmark, "One-Third (Period Three) Harmonic Generation in Microwave-Driven Josephson Tunnel Junctions", submitted to Appl. Phys. Lett.
4. N. F. Pedersen and A. Davidson, "Chaos and Noise Rise in Josephson Junctions", Appl. Phys. Lett. 39, 830-832, 1981.
5. N. F. Pedersen, M. R. Samuelson, and K. Saermark, "Parametric Excitation of Plasma Oscillations in Josephson Junctions", J. Appl. Phys. 44, 5120-5124, 1973.

This report was done with support from the Department of Energy. Any conclusions or opinions expressed in this report represent solely those of the author(s) and not necessarily those of The Regents of the University of California, the Lawrence Berkeley Laboratory or the Department of Energy.

Reference to a company or product name does not imply approval or recommendation of the product by the University of California or the U.S. Department of Energy to the exclusion of others that may be suitable.

*LAWRENCE BERKELEY LABORATORY
TECHNICAL INFORMATION DEPARTMENT
UNIVERSITY OF CALIFORNIA
BERKELEY, CALIFORNIA 94720*