Lawrence Berkeley National Laboratory

Recent Work

Title

RADIO FREQUENCY HYBRID TEES FOR NUCLEAR MAGNETIC RESONANCE

Permalink

<https://escholarship.org/uc/item/2bm1k6xr>

Authors

Klein, Melvin P.
Phelps, Donald E.

Publication Date

1967-06-01

cy. 2

University of California

Ernest O. Lawrence Radiation Laboratory

RADIO FREQUENCY HYBRID TEES FOR
NUCLEAR MAGNETIC RESONANCE

Melvin P. Klein and Donald E. Phelps

June 1967

RECEIVED
JUN 19 1967
LIBRARY
UNIVERSITY OF CALIFORNIA

TWO-WEEK LOAN COPY

This is a Library Circulating Copy
which may be borrowed for two weeks.
For a personal retention copy, call
Tech. Info. Division, Ext. 5545

UCRL-17625
cy. 2

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

Submitted to
The Review of Scientific Instruments

UCRL-17625
Preprint

UNIVERSITY OF CALIFORNIA

Lawrence Radiation Laboratory
Berkeley, California

AEC Contract No. W-7405-eng-48

RADIO FREQUENCY HYBRID TEES FOR
NUCLEAR MAGNETIC RESONANCE

Melvin P. Klein and Donald E. Phelps

June 1967

RADIO FREQUENCY HYBRID TEES FOR NUCLEAR MAGNETIC RESONANCE*

Melvin P. Klein and Donald E. Phelps

Chemical Biodynamics Laboratory, Lawrence Radiation Laboratory

University of California, Berkeley, California 94720

Prior to the advent of the microwave circulator, the majority of electron spin resonance spectrometers employed waveguide hybrid or "magic" tees as the bridge element. They provide reasonably good isolation, 40 - 50 dB, over the complete waveguide bandwidth. Coaxial hybrid tees which cover the entire radio frequency spectrum have become available recently¹. Isolation of 45 dB is common and bandwidths to several octaves can be covered in single units.

These hybrids provide an extremely simple and versatile method for assembling nuclear magnetic resonance (nmr) spectrometers for operation at virtually any frequency. Figure 1 shows the disposition of components required to assemble an nmr spectrometer around a hybrid. Radio frequency drive is supplied from a signal generator to the hybrid, and the bridge unbalance is detected by a suitable receiver. The sample coil, L , is resonated by the series combination C_1C_2 ; the ratio is adjusted to provide an impedance match to the coaxial cable connecting to the third arm of the bridge. The second arm of the hybrid is either terminated in the characteristic resistance of the hybrid or connected to a variable impedance load which can provide for finer balancing. Reactive elements in this arm introduce an additional frequency dependence.

To adjust the system the oscillator and receiver are set to the same frequency, the second arm is terminated in Z_0 , and the capacitor

C_1 is adjusted to minimize the receiver output, thus resonating the tuned circuit to the oscillator frequency. C_2 is then adjusted to further minimize the leakage. The procedure is repeated until no further reduction in leakage can be achieved. If the isolation of the hybrid has previously been established by terminating arms 2 and 3 and noting the attenuation introduced between oscillator and receiver, it suffices to continue the balancing until this isolation is achieved. Commercially available wideband modulator-mixer units provide a versatile radio frequency/^{phase}detector², whose performance frequently surpasses those constructed ad hoc in the laboratory. The phase detector may be eliminated and absorption or dispersion selected by small purposeful unbalancing of the bridge by C_2 or C_1 , respectively.

The system offers the advantages of the usual bridge arrangement, in that transmitter and receiver are well decoupled so that the system noise level is determined largely by the receiver noise figure. By comparison with the induction spectrometer³, which achieves isolation geometrically, it suffers from the frequency sensitivity of the bridge balance⁴ and the 6 dB reduction in signal arising from the division of both transmitter power and reflected signal power at the hybrid. Crystal control of the transmitter is necessary if the maximum sensitivity is to be achieved. We have observed a significant degradation in performance traceable directly to 60 Hz frequency modulation of high quality signal generators. The use of coaxial circulators, which are becoming increasingly available at lower frequencies, would restore the signal loss arising from the power divisions in the hybrid.

The simplicity of this spectrometer--only the sample resonant circuit need be constructed--recommends it for nmr measurements over a wide frequency range, for low temperature experiments where it is desirable to have only a single cable entering the cryostat, and for situations in which the ultimate in sensitivity is not required. We currently use this arrangement for field-frequency control of a high resolution nmr spectrometer at 60 MHz and anticipate using it widely for measuring and mapping the fields in superconducting solenoids. Liquid He^3 appears to be the sample of choice for this purpose, for it yields strong nmr signals with very narrow lines.

*This work was performed under the auspices of the U. S. Atomic Energy Commission.

1. Adams-Russell Co., Inc., Waltham, Mass.; Anzac Electronics, Inc., Norwalk, Conn.; Merrimac Research and Development, Inc., West Caldwell, N. J.
2. Aertech, Mountain View, Calif.; Hewlett-Packard Co., Palo Alto, Calif.
3. F. Bloch, W. W. Hansen and M. Packard, Phys. Rev. 69, 127 (1946).
4. D. T. Teaney, M. P. Klein and A. M. Portis, Rev. Sci. Instr. 32, 721 (1961).

Fig. 1

XBL 674-1055

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

- A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or
- B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.