Lawrence Berkeley National Laboratory

Recent Work

Title

Pulse Characteristics of Anthracene Scintillation Counters

Permalink

<https://escholarship.org/uc/item/6kp0d3c4>

Author

Wouters, Louis F.

Publication Date

1948-05-12

UNIVERSITY OF
CALIFORNIA

*Radiation
Laboratory*

FOR REFERENCE

NOT TO BE TAKEN FROM THIS ROOM

BERKELEY, CALIFORNIA

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

CLASSIFICATION CANCELLED BY AUTHORITY
OF THE DISTRICT ENGINEER
BY THE DECLASSIFICATION COMMITTEE

UCRL 106

Revised
Copy 1 of 3A

Pulse Characteristics of Anthracene Scintillation Counters

Louis F. Wouters
Radiation Laboratory, Dept. of Physics*
University of California
Berkeley, California

The experiments of Bell and Davis⁽¹⁾ with regard to the superiority

Bull.

(1) P. Bell and R. Davis, *Phil. Mag.* Phys. Soc. Vol. 23, No. 3

of anthracene for scintillation counters have been confirmed. In a representative arrangement, a transparent piece (1 x 1 x 1/4" in dimension) of this material is fastened to the wall of a 1P21 photomultiplier, facing the photosensitive surface. When operating at room temperature at 70 volts per stage, individual pulses up to .5 volt height (corresponding to the emission of about 100 electrons at the photosurface) are observed at the output, upon exposure to a standard radium source. The signal-to-noise ratio of about 5:1 remains essentially constant up to 120 volts per stage applied to the first two stages of the 1P21, beyond which voltage it falls rapidly; it is independent of the potential applied to the remaining seven stages. An overall gain of 25 million is then achieved by operating stages one and two at 120 volts each, and stages three through nine at 180 volts each. Pulse heights of 20 volts and more are then observed, which are sufficient to feed directly into oscilloscopes, coincidence, mixers, etc., without recourse to additional vacuum-tube amplification.

Since upwards of 1500 volts appear between adjacent anode and cathode pins, certain precautions were taken, such as slotting the base and socket, and wax impregnation. Since the peak current in the last few stages is quite high, these were by-passed with small mica capacitors.

For visual pulse observation, the photomultiplier was mounted at the neck of an oscilloscope tube of the 5JPl variety, with very short connections. The signal pulses showed a finite rise time of about .05 microsecond; this figure represents the period over which appreciable light emission by the anthracene takes place, the photomultiplier output circuit being effectively an integrator of the photoelectrons. Variation of the decrement of the output circuit (by changing the load resistor) showed that pulse height attenuation became evident for decrements lower than .15 microsecond, in agreement with the rise time observation. This figure is indicative of the resolution time to be expected in normal practice. It is significant that the rise time of noise pulses originating at the photosurface is visibly much more rapid, having no observable slope, and is much less affected by the circuit decrement.

Typical values for the output circuit elements:

circuit capacitance	-- 15 micromicrofarads
load resistance	-- 10,000 ohms

The author wishes to acknowledge the encouragement and interest of Professors E. O. Lawrence and R. L. Thornton and the cooperation of the laboratory staff in pursuing these investigations. He also wishes especially to thank Messrs. Bell and DeBenedetti of the Oak Ridge National Laboratory for the clear, crystallized anthracene initially used in the described tests.

* This letter is based on work performed at the Radiation Laboratory under Contract No. W-4205-eng-48 with the Atomic Energy Commission.