Lawrence Berkeley National Laboratory

Recent Work

Title

A HIGH-DUTY-CYCLE ONE-SHOT MULTIVIBRATOR CIRCUIT

Permalink

<https://escholarship.org/uc/item/7436h8m8>

Author

Hale, Duane O.

Publication Date

1960-07-11

UNIVERSITY OF
CALIFORNIA

Ernest O. Lawrence

*Radiation
Laboratory*

TWO-WEEK LOAN COPY

*This is a Library Circulating Copy
which may be borrowed for two weeks.
For a personal retention copy, call
Tech. Info. Division, Ext. 5545*

BERKELEY, CALIFORNIA

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

For Pub. R. S. I.

UCRL-9286

Limited distribution

UNIVERSITY OF CALIFORNIA

Lawrence Radiation Laboratory
Berkeley, California

Contract No. W-7405-eng-48

A HIGH-DUTY-CYCLE ONE-SHOT MULTIVIBRATOR CIRCUIT

Duane O. Hale

July 11, 1960

A HIGH-DUTY-CYCLE ONE-SHOT MULTIVIBRATOR CIRCUIT*

Duane O. Hale

Lawrence Radiation Laboratory
University of California
Berkeley, California

July 11, 1960

* This work was done under the auspices of the U. S. Atomic Energy Commission.

The one-shot multivibrator commonly used as a delay, gating, and pulse-shaping unit suffers a main disadvantage of low-duty-cycle operation, because of its long recovery time. The one-shot circuit (Fig. 1) described below is capable of a 95% duty cycle.

A negative pulse applied to the base of Q1 turns Q1 on, and the positive signal appearing at the collector of Q1 turns Q2 off through C_1 . As Q2 conducts less, Q1 is allowed to conduct more, and this process continues until cutoff of Q2 and saturation of Q1 is reached. Then C_1 begins charging through R_2 until the base of Q2 reaches its emitter potential. At this time, Q2 turns on and drives Q1 off through the common emitter connection. Now C_1 must discharge through the base resistance of Q2--which is low since it is turning on--and R_1 . Since R_1 is a fairly large resistance, C_1 would normally take a good portion of the duty cycle discharging to its original state. However, the output pulse which went negative at the beginning of the cycle is now going positive and is applied through the differentiating network C_2 and R_3 to the base of Q3. When Q3 turns on R_1 is momentarily shorted, allowing C_1 to discharge to its original charge in approximately 5% of the duty cycle. The circuit is now ready to be triggered again.

The diode in the base circuit of Q3 eliminates the negative portion of the differentiated signal at the base of Q3.

* This work was done under the auspices of the U. S. Atomic Energy Commission.

One of these circuits is now used at Berkeley as an off gate and might be found useful in computing or pulse-shaping circuits where loss of duty cycle is not desirable.

FIGURE LEGEND

Fig. 1. (a) Schematic diagram of improved one-shot circuit. (b) Typical oscilloscope trace for normal one-shot operation simulated by removing Q3. The signal was taken off at point A in the schematic diagram. (c) Signal at A with Q3 in the circuit.

(a)

(b)

(c)