

# Lawrence Berkeley National Laboratory

## LBL Publications

### Title

Crossing of an Incoherent Integral Resonance in the Electron Ring Accelerator

### Permalink

<https://escholarship.org/uc/item/5d49w0bn>

### Authors

Pellegrini, Claudio

Sessler, Andrew M

### Publication Date

1970

### Copyright Information

This work is made available under the terms of a Creative Commons Attribution License, available at <https://creativecommons.org/licenses/by/4.0/>

Submitted to Nuclear Inst. and Methods

UCRL-19462  
Preprint

c.2

RECEIVED  
LAWRENCE  
RADIATION LABORATORY

APR 8 1970

LIBRARY AND  
DOCUMENTS SECTION

CROSSING OF AN INCOHERENT INTEGRAL RESONANCE  
IN THE ELECTRON RING ACCELERATOR

Claudio Pellegrini and Andrew M. Sessler

January 26, 1970

AEC Contract No. W-7405-eng-48

TWO-WEEK LOAN COPY

*This is a Library Circulating Copy  
which may be borrowed for two weeks.  
For a personal retention copy, call  
Tech. Info. Division, Ext. 5545*

LAWRENCE RADIATION LABORATORY  
UNIVERSITY of CALIFORNIA BERKELEY

UCRL-19462

28

## **DISCLAIMER**

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

CROSSING OF AN INCOHERENT INTEGRAL RESONANCE

IN THE ELECTRON RING ACCELERATOR\*

Claudio Pellegrini† and Andrew M. Sessler

Lawrence Radiation Laboratory  
University of California  
Berkeley, California

January 26, 1970

ABSTRACT

In one mode of operation of an electron ring accelerator (ERA), at the end of compression rings are slowly moved through the radial integral betatron resonance  $Q_r = 1$ . Although the coherent radial oscillation frequency of the ring as a whole remains below unity, the oscillation frequencies of individual electron are (incoherently) caused to pass through the resonance because of the additional focusing from ions trapped in the ring. In this paper the effect of field errors on ring major and minor radii is evaluated--theoretically--for the cases in which the spread in the square of the electron oscillation frequency ( $\Delta^2$ ) is (a) much larger and (b) much smaller than the contribution to the square of the oscillation frequency from the ions ( $\Lambda^2$ ). It is shown that for the ERA, where case (b) applies, the increase in ring minor dimensions, for given field errors and rate of resonance crossing, is less than in case (a) by a factor of  $(\Delta/\Lambda)^2$ . Numerical examples show that the degradation of ring quality in case (b) should, with suitable attention to the design and construction of the ERA apparatus, be acceptably small.

## 1. INTRODUCTION

In the electron ring accelerators (ERA) now being studied at Dubna, Berkeley, Karlsruhe, and Garching,<sup>1)</sup> an electron ring is compressed in a magnetic field having field index  $n \equiv -\frac{r}{B} \frac{\partial B}{\partial r}$  such that  $0 < n < 1$ . At the end of compression positive ions are captured in the ring, which is subsequently extracted from the compressor and brought into an accelerating column having a constant magnetic field and hence  $n = 0$ .

During the compression process the radial betatron frequency  $\omega_r = Q \Omega$ , where  $\Omega$  is the revolution frequency and  $Q$  is approximately given by  $(1 - n)^{1/2}$ , stays below  $\Omega$  or, equivalently,  $Q$  stays below unity. The capture of ions in the electron ring introduces an additional focusing force on the electron, which has the effect of increasing  $Q$ . During the extraction process  $n$  goes to zero, so that, in the absence of ions or other additional forces,  $Q$  would become equal to unity. As a result of both effects  $Q$  crosses the value  $Q = 1$ .

As is well known, when  $Q = 1$  an integer resonance is excited. This can produce a large displacement of the electron orbits and hence a beam loss. Moreover, even if the beam is not lost it is possible that the crossing of the resonance could produce a large increase in beam dimension and a corresponding decrease in the electric field that keeps the ions inside the ring. As a consequence, the external electric field which is applied so as to accelerate the ring would have to be lowered to an uninterestingly small value.

The increase in oscillation amplitude of a single particle crossing an integral resonance at a rate  $r = \frac{d\omega_r}{dt}$  is given approximately by

$$x_s = \left( \frac{\pi}{\Omega r} \right)^{1/2} R \Omega^2 \left( \frac{\Delta B}{B} \right), \quad (\text{I-1})$$

where  $R$  is the beam radius,  $\Omega$  the revolution frequency, and  $(\Delta B/B)$  the magnetic field perturbation driving the resonance<sup>2-5</sup>.

Formula (I-1) shows, using typical ERA parameters, that in order to maintain the increase in amplitude within reasonable limits, the requirements on the magnetic field are very strong; for instance, assuming  $x_s = 0.1$  cm,  $R = 3$  cm, and  $\dot{Q} = 10^4$  sec<sup>-1</sup>, one has  $(\Delta B/B) < 10^{-5}$ . Various possibilities have been suggested for reducing  $Q$ , so as to avoid crossing the resonance: The use of image forces obtained by surrounding the electron ring with a dielectric cylinder<sup>6)</sup> or a slotted metallic cylinder<sup>7)</sup>, or keeping  $Q > 1$  throughout compression and acceleration of the ring by using the azimuthal magnetic field generated by a current along the axis of the ring<sup>8)</sup>.

The use of image forces seems to provide a practical way to avoid the resonance crossing when there are only few ions in the ring, but not when the ring is charged with more ions than of the order of 1% of the electrons. The use of an azimuthal magnetic field to keep  $Q$  always above unity requires currents in the conductor on the axis of the order of  $10^5$  A --an inconvenient, but possible, design requirement.

It has, however, been pointed out by Van der Meer<sup>9)</sup>, on the basis of qualitative arguments, that the application to the ERA of the formula for the single-particle increase of amplitude during the resonance crossing may be incorrect. In this paper we study the effect

of resonance crossing in detail. In particular we consider the case when  $Q$  would stay below unity in the absence of ions (i.e., the coherent integral resonance is not crossed), but is shifted above unity by the ion focusing force (i.e., the incoherent integral resonance is crossed). We find that in this case the formula (I-1) is not valid and that the behavior of the beam in crossing the incoherent resonance depends on the ratio of the spread in the square of the frequency in the electron ring,  $\Delta^2$ , to the shift in the square of the frequency,  $\Lambda^2$ , induced by the ions.

The results described by (I-1) applies only when the condition

$$\frac{\Delta^2}{\Lambda^2} \gg 1, \quad (\text{I-2})$$

since in this case each electron behaves as a single electron having a frequency  $(\omega^2 + \Lambda^2)^{1/2}$ , where  $\omega$  is the frequency due to the external magnetic field and image forces, and  $\Lambda$  is the shift in frequency caused by the ions. Thus resonance crossing leads to an increase in beam minor dimensions, but no change in the beam center of mass.

On the contrary, in the case more often encountered in the ERA, when

$$\frac{\Delta^2}{\Lambda^2} \ll 1, \quad (\text{I-3})$$

there is a (small) change in the local beam center of mass, but the beam minor dimension increase is smaller, by a factor of  $(\Delta^2/\Lambda^2)$ , than that expected on the basis of (I-1). Hence the limit on the tolerable magnetic field imperfections,  $\Delta B/B$  (which is set by the strong requirement of small minor dimensions of the ring), is lowered and can more

easily be satisfied. Thus our detailed analysis supports the general conclusions of Van der Meer and is in qualitative agreement with observation<sup>10</sup>.

That the simple formula (I-1) does not apply to circular electron beams partially or totally neutralized by ions is of importance, also, for electron storage rings. In this case, too, due to the long beam lifetime, a large number of ions are captured by the beam, when clearing field electrodes are not used. Once again, the frequency shift introduced by the ions can cause a crossing of an integer resonance. Both the conditions that  $Q$  remain below the nearest integer during the ion loading process and condition (I-3) are well satisfied in storage rings. However, in this paper we have considered only azimuthally uniform beams, while the electron beam of a storage ring is bunched. Hence, we cannot directly apply our results to storage rings. Notwithstanding, we think that, at least to a first approximation, the results of this work indicate that also in the case of the storage ring the crossing of the resonance produces only a beam widening, and that this widening is not too dangerous because of the strong reduction introduced by the factor  $\Delta^2/\Lambda^2$ . This conclusion is in agreement with the experimental observations performed on electron storage rings.

## 2. FORMULATION OF THE PROBLEM

We assume that the electrons move on a circular orbit with a constant angular velocity  $\Omega$ , and that they oscillate in a direction orthogonal to this orbit under the action of the focusing forces due to the external magnetic field and to the ions. The ions are assumed to have zero angular velocity and to oscillate in the same direction as



the electrons under the action of the focusing force due to the electrostatic field of the electrons. We ignore ion-ion forces, since in practice the ion density is sufficiently low that these terms are negligible.

Let us call  $x_k$ ,  $\theta_k$  and  $\xi_j$ ,  $\psi_j$  the transverse and the azimuthal coordinates of the  $k$ th electron and  $j$ th ion. The equations of motion can be written as

$$\begin{aligned} \ddot{x}_k(t) + \omega_k^2(t)x_k(t) + \Lambda_k^{(i)2}(t)[x_k(t) - \bar{\xi}(t, \theta_k)] \\ + \Lambda_k^{(e)2}(t)[x_k(t) - \bar{x}(t, \theta_k)] &= a \cos(\bar{n}\theta_k + \phi), \\ \theta_k &= \Omega t + \alpha_k, \\ \ddot{\xi}_j(t) + M_j^2[\xi_j(t) - \bar{x}(t, \psi_j)] &= 0, \\ \psi_j &= \text{const}, \end{aligned} \tag{II-1}$$

where  $\omega_k^2 x_k$  is the focusing force due to the magnetic field, the  $\Lambda_k^{(e)2}$  term describes the force of electron on electrons,  $\Lambda_k^{(i)2}[x_k - \bar{\xi}(t, \theta_k)]$  and  $M_j^2[\xi_j - \bar{x}(t, \psi_j)]$  are the forces between ions and electrons and  $a \cos(\bar{n}\theta_k + \phi)$  is the perturbation in the guide magnetic field. Note that we consider only field bump errors and do not include gradient error terms as they are--in practice--negligible<sup>4)</sup>. We consider only the  $\bar{n}$ -Fourier component in the magnetic field perturbation, where  $n \Omega \simeq \omega_k$ .

The electron-ion forces are written, in the linear approximation, as proportional to the distance of the  $k$ th particle from the local center of mass of the particles of the other species,  $\bar{x}(t, \theta)$  and

$\bar{\xi}(t, \psi)$ . The local center of mass can be defined, with the help of the step function  $S(\theta)$ , as

$$\bar{x}(t, \theta) = \frac{\sum_k x_k(t) S(\theta_k - \theta) S(\theta + d\theta - \theta_k)}{\sum_k S(\theta_k - \theta) S(\theta + d\theta - \theta_k)},$$

$$\bar{\xi}(t, \psi) = \frac{\sum_j \xi_j(t) S(\psi_j - \psi) S(\psi + d\psi - \psi_j)}{\sum_j S(\psi_j - \psi) S(\psi + d\psi - \psi_j)}.$$
(II-2)

The nonlinearities of this force, as well as the nonlinearities in the external focusing force, are taken into account approximately by allowing a dependence of  $\omega^2$ ,  $M^2$ ,  $\Lambda^{(e)2}$ , and  $\Lambda^{(i)2}$  on some of the parameters of the particles such as oscillation amplitude or energy. Newton's third law implies a subsidiary condition amongst the  $\Lambda_k^{(i)}$  and  $M_j$ . We need not invoke this relation, as will be seen below.

The quantities  $\omega_k$ ,  $M_j$ ,  $\Lambda_k^{(e)}$ , and  $\Lambda_k^{(i)}$  are functions of time, because of the changes in the external magnetic field and in the number of ions with time. Both these variations are assumed to be very slow compared with the electron and ion oscillation period.

We are only interested in studying the closed-orbit perturbations due to the magnetic field imperfections, i.e., the particular solution of the nonhomogenous (II-1).

We will first consider the case in which  $\omega_k$ ,  $\Lambda_k^{(e)}$ ,  $M_k$ , and  $\Lambda_k^{(i)}$  are constant in time. Since the driving force,  $a \cos(\bar{n}\theta + \phi)$ ,

is periodic with respect to  $\theta$ , we look for a solution having the same periodicity. Let us assume

$$\begin{aligned} x_k(t) &= A_k \cos(\bar{n} \theta_k + \phi), \\ \xi_j(t) &= B_j \cos(\bar{n} \psi_j + \phi). \end{aligned} \tag{II-3}$$

The local centers of mass are then given by

$$\begin{aligned} \bar{x}(t, \theta) &= \bar{A} \cos(\bar{n}\theta + \phi), \\ \bar{\xi}(t, \psi) &= \bar{B} \cos(\bar{n}\psi + \phi). \end{aligned} \tag{II-4}$$

The amplitudes  $\bar{A}$ ,  $\bar{B}$  are given, in the case of a beam containing  $N_e$  electron and  $N_i$  ions uniformly distributed along the circumference, and assuming that the distribution of the  $A_k$ ,  $B_k$  is independent of the azimuthal position, by

$$\begin{aligned} \bar{A} &= \left( \frac{1}{N_e} \right) \sum_{k=1}^{N_e} A_k, \\ \bar{B} &= \left( \frac{1}{N_i} \right) \sum_{j=1}^{N_i} B_j. \end{aligned} \tag{II-5}$$

Substituting (II-3) and (II-4) into (II-1), we obtain

$$\begin{aligned} B_j &= \bar{A}, \\ A_k \left\{ \omega_k^2 + \Lambda_k^{(e)2} + \Lambda_k^{(i)2} - \bar{n}^2 \Omega^2 \right\} - \Lambda_k^{(e)2} \bar{A} - \Lambda_k^{(i)2} \bar{B} &= a. \end{aligned} \tag{II-6}$$

By use of (II-5), the system of (II-6) can be reduced to

$$A_k \left\{ \omega_k^2 + \Lambda_k^{(e)2} + \Lambda_k^{(i)2} - \bar{n}^2 \Omega^2 \right\} - \Lambda_k^{(i)2} \bar{A} - \Lambda_k^{(e)2} \bar{A} = a. \quad (\text{II-7})$$

The first of (II-6), together with (II-5), shows simply that, under the action of the external perturbation, the local ion center of mass undergoes the same displacement as the local electron center of mass.

This result is also valid for slow changes of  $\omega_k$ ,  $M_k$ ,  $\Lambda_k^{(e)}$ , and  $\Lambda_k^{(i)}$ , so that in general we can reduce the equations of (II-1) to an equation for the electrons only, namely

$$\ddot{x}_k + \omega_k^2(t)x_k + \Lambda_k^2(t)[x_k - \bar{x}] = a \cos(\bar{n}\theta_k + \phi), \quad (\text{II-8})$$

where we have set  $\Lambda_k^2 = \Lambda_k^{(e)2} + \Lambda_k^{(i)2}$ . When  $\omega_k$  and  $\Lambda_k$  are constant in time this clearly reduces to (II-7).

### 3. NORMAL MODE ANALYSIS

We have reduced the problem to solving (II-8), which task is accomplished in this and the next two sections. We can limit ourselves to the case in which the variation in time of  $\omega_k$  and  $\Lambda_k$  is small compared with  $\bar{n}\Omega$ . It is then possible to perform a power-series expansion of these quantities, and to consider only terms up to first order, namely, to write

$$\begin{aligned} \omega_k^2 &= \omega_k^2(t_0) + r(t - t_0), \\ \Lambda_k^2 &= \Lambda_k^2(t_0) + r'(t - t_0). \end{aligned} \quad (\text{III-1})$$

We also assume that  $r$  and  $r'$  are different from zero only in a time

interval  $t_0 - t_1$  during which the resonance is crossed, and that the initial and final values of  $\omega_k^2$  and  $\omega_k^2 + \Lambda_k^2$  are respectively well below and well above the resonant value  $\bar{n}\Omega^2$ . Notice, also, that we have assumed  $r$  and  $r'$  to be equal for all particles. This is a good approximation when the frequency spreads for both  $\omega$  and  $\Lambda$  are small compared with  $\bar{n}\Omega$ .

We can now obtain a solution of (II-8), assuming  $x_k$  to be of the form

$$x_k(t) = \sum_{n=1}^{N_e} A_n(t) C_k^{(n)} \exp[i(n\bar{n}\theta_k + \phi)], \quad (\text{III.2})$$

where the  $A_n(t)$  are unknown functions and the  $C_k^{(n)}$  are a complete orthonormal set of vectors defined as the eigenvectors of the linear system of equations

$$\begin{aligned} [\omega_k^2(t_0) + \Lambda_k^2(t_0)] C_k^{(n)} - \Lambda_k^2(t_0) \bar{C}^{(n)} \\ = \Gamma_{(n)}^2 C_k^{(n)}, \quad n = 1, \dots, N_e, \end{aligned} \quad (\text{III-3})$$

where  $\bar{C}^{(n)}$  is defined as

$$\bar{C}^{(n)} = \frac{1}{N_e} \sum_{k=1}^{N_e} C_k^{(n)},$$

as follows from (II-2) and (III-2); and  $\Gamma_{(n)}^2$  is an eigenvalue.

Substituting (III-2) into (II-8) and using (III-1) and (III-3), we get

$$\sum_{n=1}^{N_e} \left\{ \ddot{A}_n + 2i\bar{n}\Omega \dot{A}_n + [\Gamma_{(n)}^2 - \bar{n}^2\Omega^2 + (r+r')(t-t_0)]A_n \right\} C_k^{(n)} - r'(t-t_0) \sum_n A_n \bar{C}^{(n)} = a. \quad (\text{III-4})$$

Using the orthonormality property of the  $C_k^{(n)}$ , we obtain

$$\ddot{A}_n + 2i\bar{n}\Omega \dot{A}_n + [\Gamma_{(n)}^2 - \bar{n}^2\Omega^2 + (r+r')(t-t_0)]A_n - r'(t-t_0)N_e \sum_{m=1}^{N_e} A_m \bar{C}^{(m)} \bar{C}^{(n)} = aN_e \bar{C}^{(n)}. \quad (\text{III-5})$$

We assume that  $A_n(t)$  is a function varying slowly with respect to the characteristic oscillation periods, so that it is possible to neglect the second derivative of  $A_n(t)$  in (III-5) and write it as

$$2i\bar{n}\Omega \dot{A}_n + [\Gamma_{(n)}^2 - \bar{n}^2\Omega^2 + (r+r')(t-t_0)]A_n - r'(t-t_0)N_e \sum_{m=1}^{N_e} A_m \bar{C}^{(m)} \bar{C}^{(n)} = aN_e \bar{C}^{(n)}. \quad (\text{III-6})$$

The problem is now reduced to finding the  $C_k^{(n)}$  and  $A_n(t)$ , i.e., to solving (III-3) and (III-6).

The solution will depend on the ratio  $\Delta^2/\Lambda_0^2$ , where  $\Delta^2$  is the width of the distribution of the frequencies  $\omega_k^2$ , and  $\Lambda_0^2$  is the average value of  $\Lambda_k^2$ . (We assume that the widths of the distribution of  $\omega_k$  and  $\Lambda_k$  are small compared with the average values of  $\omega_k$  and  $\Lambda_k$ .)

In the remainder of this paper we will study only the two cases

$$(a) \quad \frac{\Delta^2}{\Lambda_0^2} \ll 1,$$

and

$$(b) \quad \frac{\Delta^2}{\Lambda_0^2} \gg 1,$$

for both of which solutions of (III-3) and (III-6) can be obtained.

We also notice that we are interested in the determination of the two quantities

$$\bar{x} = \left| \frac{1}{N_e} \sum_k x_k \right| = \left| \sum_n A_n(t) \bar{c}^{(n)} \right| \quad (III-7)$$

and

$$\delta = \left\{ \frac{1}{N_e} \sum_k |x_k - \bar{x}|^2 \right\}^{1/2} = \left\{ \frac{1}{N_e} \sum_n |A_n(t)|^2 - \bar{x}^2 \right\}^{1/2}, \quad (III-8)$$

which are the local center-of-mass amplitude and the root-mean-square (rms) beam size. Both  $\bar{x}$  and  $\delta^2$ , as well as (III-6), depend on the  $c_k^{(n)}$  only through the average values  $\bar{c}^{(n)}$ .

#### 4. DETERMINATION OF THE EIGENVECTORS

In this section we determine the eigenvectors and eigenvalues of (III-3) in the two cases: (a)  $\Delta^2/\Lambda_0^2 \ll 1$ , and (b)  $\Delta^2/\Lambda_0^2 \gg 1$ . We consider case (a) first; case (b) is rather trivial and is discussed at the end of this section. It is convenient to start by solving (III-3) for the case of zero frequency spread. The eigenvectors  $c_k^{(n)0}$  are given, for  $\Delta = 0$ , by

$$c_k^{(n)0} = \frac{1}{\sqrt{N}} e^{2\pi i n k / N}, \quad (\text{IV-1})$$

$$\bar{c}_k^{(n)0} = \frac{1}{\sqrt{N}} \delta_{n,0}, \quad (\text{IV-2})$$

where we have employed  $N$  as a notation for  $N_e$ . The corresponding eigenvalues are

$$\Gamma_{(n)0}^2 = \omega_0^2 + \Lambda_0^2 [1 - \delta_{n,0}]. \quad (\text{IV.3})$$

Notice that all the  $\Gamma_{(n)}$  are equal, with the exception of  $\Gamma_{(0)}$ .

For a small frequency spread, we can use perturbation theory to determine the  $c_k^{(n)}$ . Let us rewrite Eq. (III-3) as

$$\left( \tilde{H}^{(0)} + \tilde{H}^{(1)} \right) \tilde{c}^{(n)} = \Gamma_{(n)}^2 \tilde{c}^{(n)}, \quad (\text{IV-4})$$

where  $\tilde{c}^{(n)}$  is a vector of components  $c_k^{(n)}$ ,

$$\tilde{H}_{kl}^{(0)} = (\omega_0^2 + \Lambda_0^2) \delta_{kl} - \frac{\Lambda_0^2}{N}, \quad (\text{IV-5})$$

$$\tilde{H}_{kl}^{(1)} = (\omega_k^2 + \Lambda_k^2 - \omega_0^2 - \Lambda_0^2) \delta_{kl} - \frac{\Lambda_k^2 - \Lambda_0^2}{N}, \quad (\text{IV-6})$$

and  $\omega_0^2$  and  $\Lambda_0^2$  are the average values of  $\omega_k^2$ ,  $\Lambda_k^2$ . For  $\tilde{H}^{(1)} = 0$ ,  $\tilde{c}^{(n)}$  is equal to  $\tilde{c}^{(n)0}$  as given by (IV-1), and  $\Gamma_{(n)}^2 = \Gamma_{(n)0}^2$  as given by (IV-3).

To apply perturbation theory when  $\tilde{H}^{(1)} \neq 0$ , one must remember that the unperturbed solution is degenerate (all eigenfunctions, except  $\tilde{c}^{(0)0}$ , belong to the same eigenvalue), and use instead of



the  $\zeta^{(n)0}$ 's, for  $n \neq 0$ , a linear combination of these vectors such that  $\underline{H}^{(1)}$  is diagonalized. Calling these new vectors  $\phi^{(n)}$ , one has

$$\phi^{(0)} = \zeta^{(0)0}, \quad (\text{IV-7})$$

and

$$\phi^{(n)} = \sum_{t=1}^{N-1} B_t^n \zeta^{(t)0} \quad \text{for } n \neq 0, \quad (\text{IV-8})$$

where

$$B_t^n = \frac{1}{(N-1)^{1/2}} e^{2\pi i n t / (N-1)}. \quad (\text{IV-9})$$

It is easy to verify that

$$\left( \phi^{*(n)} \underline{H}^{(1)} \phi^{(m)} \right) = 0; \quad n, m \neq 0 \quad \text{and} \quad n \neq m, \quad (\text{IV-10})$$

and

$$\begin{aligned} \left( \phi^{*(n)} \underline{H}^{(1)} \phi^{(n)} \right) &= \frac{1}{N} \sum_{k=0}^{N-1} \sum_{t=1}^{N-1} (\omega_k^2 + \Lambda_k^2 - \omega_0^2 - \Lambda_0^2) \\ &\times \left\{ \exp 2\pi i t \left[ \frac{n}{N-1} + \frac{k}{N} \right] \right\}; \quad n \neq 0, \end{aligned} \quad (\text{IV-11})$$

and that

$$\begin{aligned} \left( \phi^{*(0)} \underline{H}^{(1)} \phi^{(n)} \right) &= \frac{1}{N} \sum_{k=0}^{N-1} \sum_{t=1}^{N-1} (\omega_k^2 - \omega_0^2) \\ &\times \frac{1}{(N-1)^{1/2}} \left\{ \exp 2\pi i t \left[ \frac{n}{N-1} + \frac{k}{N} \right] \right\}. \end{aligned} \quad (\text{IV-12})$$

The solution of (IV-4) is now given by

$$\zeta^{(n)} = \phi^{(n)} + \sum_{m \neq n} A_m^n \phi^{(m)}, \quad (\text{IV-13})$$

and, to first order in the perturbation, one has

$$A_m^n = \frac{\left( \phi^{*(m)} \mathbb{H}^{(1)} \phi^{(n)} \right)}{\Gamma_{(n)}^2 - \Gamma_{(m)0}^2}, \quad (\text{IV-14})$$

$$\Gamma_{(n)}^2 = \Gamma_{(n)0}^2 + \left( \phi^{*(n)} \mathbb{H}^{(1)} \phi^{(n)} \right). \quad (\text{IV-15})$$

Notice that with our choice of  $\omega_0^2$ ,  $\Lambda_0^2$  one has also

$$\left( \phi^{*(0)} \mathbb{H}^{(1)} \phi^{(0)} \right) = 0,$$

so that there is no first-order correction to the coherent frequency  $\Gamma_{(0)}^2$ . The quantities  $\bar{c}^{(n)}$  are now easily obtained, and, to first order, one has

$$\bar{c}^{(0)} = \frac{1}{\sqrt{N}} + \text{first order term}, \quad (\text{IV-16})$$

$$\bar{c}^{(n)} = \frac{1}{\sqrt{N}} \frac{\left( \phi^{*(0)} \mathbb{H}^{(1)} \phi^{(n)} \right)}{\Lambda_0^2} \quad (\text{IV-17})$$

$$= \frac{1}{N \Lambda_0^2} \sum_{k=0}^{N-1} \sum_{t=1}^{N-1} (\omega_k^2 - \omega_0^2)$$

$$\times \frac{1}{(N(N-1))^{1/2}} \left\{ \exp 2\pi i t \left[ \frac{k}{N} + \frac{n}{N-1} \right] \right\}.$$

We can now use these results to simplify (III-6). In the case  $n = 0$  the equation contains zero-order terms and first-order terms in  $\Delta^2/\Lambda_0^2$ . Neglecting the first-order terms, one has

$$2i\bar{n}\Omega \dot{A}_0 + [\omega_0^2 - \bar{n}^2\Omega^2 + r(t - t_0)] A_0 = a\sqrt{N}. \quad (\text{IV-18})$$

For  $n \neq 0$  (III-6) contains first- and second-order terms in  $\Delta^2/\Lambda_0^2$ . Keeping only lowest-order terms, one has

$$2i\bar{n}\Omega \dot{A}_n + [\omega_0^2 + \Lambda_0^2 - \bar{n}^2\Omega_0^2 + (r + r')(t - t_0)] A_n - r'(t - t_0)\sqrt{N} \bar{C}^{(n)} A_0 = a N \bar{C}^{(n)}. \quad (\text{IV-19})$$

In case (b) the coupling between particles is negligible and the eigenvalues are almost equal to the single particle frequencies, i.e.,

$$\Gamma_{(n)}^2 = \omega_n^2 + \Lambda_n^2 + o[(\Lambda_0^2/\Delta^2)^2]. \quad (\text{IV-20})$$

The corresponding eigenfunctions are

$$C_k^{(n)} = \delta_{n,k} + o[(\Lambda_0^2/\Delta^2)], \quad (\text{IV-21})$$

and the  $\bar{C}^{(n)}$  are given, to lowest order, by

$$\bar{C}^{(n)} = \frac{1}{N}. \quad (\text{IV-22})$$

Equation (III-6) now becomes, neglecting the coupling between particles,

$$2i\bar{n}\Omega \dot{A}_n + [\omega_n^2 + \Lambda_n^2 - \bar{n}^2\Omega^2 + (r + r')(t - t_0)] A_n = a. \quad (\text{IV-23})$$

5. DETERMINATION OF THE AMPLITUDE FUNCTIONS

In this section we solve (IV-18), (IV-19), (IV-23) for the functions  $A_n(t)$ .

5.1. Case b

We start from (IV-23), which we write in the form

$$\dot{A}_n(t) - i g_n(t) A_n(t) = -i \bar{a}, \quad (V-1)$$

where

$$g_n(t) = \frac{1}{2n\Omega} [\omega_n^2 + \Lambda_n^2 - n^2\Omega^2 + (r + r')(t - t_0)], \quad (V-2)$$

$$\bar{a} = \frac{a}{2n\Omega}. \quad (V-3)$$

The solution of (V-1), with the initial condition  $A(t_0) = 0$ ,

is

$$A_n(t) = -i\bar{a} \left\{ \exp \left[ i \int_{t_0}^t g_n(t') dt' \right] \right\} \int_{t_0}^t dt' \exp \left[ -i \int_{t_0}^{t'} g_n(t'') dt'' \right]. \quad (V-4)$$

Evaluating the integrals, and using the notation

$$D_n = (\omega_n^2 + \Lambda_n^2 - n^2\Omega^2)/2n\Omega,$$

$$p = (r + r')/2n\Omega, \quad (V-5)$$

one has:

$$\int_{t_0}^t \exp \left\{ -i \left[ D_n(t' - t_0) + \frac{1}{2} p(t' - t_0)^2 \right] \right\} dt' \\ = \sqrt{\frac{\pi}{p}} \exp[iD_n^2/(2p)] \left\{ h \left( \frac{p(t - t_0) + D_n}{\sqrt{\pi p}} \right) - h \left( \frac{D_n}{\sqrt{\pi p}} \right) \right\}, \quad (V-6)$$

where

$$h(x) = C(x) - i S(x), \quad (V-7)$$

and  $C(x)$ ,  $S(x)$  are the Fresnel integrals.

It is usually possible, when  $p$  is small and the integral extends from well below to well above the resonance, to make the approximation

$$\frac{D_n}{\sqrt{\pi p}} \ll -1, \quad (V-8)$$

$$\frac{p(t - t_0) + D_n}{\sqrt{\pi p}} \gg 1.$$

Since  $C(\pm \infty) = S(\pm \infty) = \pm \frac{1}{2}$ , one has in this case

$$\int_{t_0}^t \exp \left\{ -i \left[ D_n (t' - t_0) + \frac{1}{2} p (t' - t_0)^2 \right] \right\} dt'$$

$$\approx \left( \frac{2\pi}{p} \right)^{1/2} \exp \left[ +i (D_n^2 / 2p) - i\pi/4 \right]. \quad (V-9)$$

The value of  $A_n$  after crossing the resonance is then given by

$$A_n \approx -i\bar{a} \left( \frac{2\pi}{p} \right)^{1/2} \exp \left\{ i \left[ D_n (t - t_0) + \frac{p}{2} (t - t_0)^2 \right] \right\} \exp \left[ +i (D_n^2 / 2p) - i\pi/4 \right]$$

$$= -i\bar{a} \left( \frac{2\pi}{p} \right)^{1/2} \exp \left\{ i \left[ \frac{p(t - t_0) + D_n}{\sqrt{2p}} \right]^2 - i\pi/4 \right\}. \quad (V-10)$$

The final amplitude after crossing the resonance is therefore

$$|A_n| = \bar{a} \left( 2\pi/p \right)^{1/2} = a \left[ \pi/\bar{n}\Omega(r + r') \right]^{1/2}, \quad (V-11)$$

a well-known result.

### 5.2. Case a

In this case the frequency spread  $\Delta^2$  is small compared with the frequency shift  $\Lambda_0^2$ . The situation is described by (IV-18) and (IV-19), and is clearly more complicated than case (b). The procedure is to solve (IV-18) for  $A_0$ , substitute the result in (IV-19), and solve for  $A_n$ . The result will be different according to whether the coherent frequency,  $\omega_0$ , does or does not cross the resonance. We will consider here only the case in which  $\omega_0$  does not cross the resonance (i.e., the coherent integral resonance is not crossed), since this is the situation which usually confronts us in practice. Under this assumption one can neglect the variation in time of the coherent frequency and of  $A_0$ , and obtain from (IV-18)

$$A_0 = \frac{a\sqrt{N}}{\omega_0^2 - (\bar{n}\Omega)^2}. \quad (V-12)$$

Substituting this in (IV-19) one obtains

$$\dot{A}_n - i(D + p(t - t_0))A_n = -i\bar{a}N\bar{C}^{(n)}[1 + q(t - t_0)], \quad (V-13)$$

where

$$D = \frac{\omega_0^2 + \Lambda_0^2 - \bar{n}^2\Omega^2}{2\bar{n}\Omega},$$

$$p = \frac{r + r'}{2\bar{n}\Omega},$$

$$\bar{a} = \frac{a}{2\bar{n}\Omega},$$

$$q = \frac{r'}{\omega_0^2 - \bar{n}^2\Omega^2}. \quad (V-14)$$

The solution can again be written, assuming  $A_n(t_0) = 0$ , as

$$A_n(t) = -i \bar{a} N \bar{c}^{(n)} \exp \left\{ i \int_{t_0}^t [D + p(t' - t_0)] dt' \right\} \\ \times \int_{t_0}^t dt' [1 + q(t' - t_0)] \exp \left\{ -i \int_{t_0}^{t'} [D + p(t'' - t_0)] dt'' \right\}. \quad (V-15)$$

The integrals of (V-15) can be evaluated by using (V-6) and

$$\int_{t_0}^t dt' (t' - t_0) \exp \left\{ -i [D(t' - t_0) + \frac{p}{2}(t' - t_0)^2] \right\} \\ = \frac{2}{p} e^{i(D^2/2p)} \left\{ -\frac{D}{2\sqrt{\pi p}} \left[ h \left( \frac{p(t - t_0) + D}{\sqrt{\pi p}} \right) - h \left( \frac{D}{\sqrt{\pi p}} \right) \right] \right. \\ \left. + \frac{1}{2} \left[ \sin \left( \frac{p(t - t_0) + D}{\sqrt{2p}} \right)^2 + i \cos \frac{D^2}{2p} \right] \right\}. \quad (V-16)$$

Assuming the conditions (V-8) to be satisfied, one obtains an amplitude, after crossing the resonance,

$$A_n(t) \approx -i \bar{a} N \bar{c}^{(n)} \left( \frac{2\pi}{p} \right)^{1/2} \left\{ 1 - \frac{qD}{\pi p} \right\} \exp \left\{ i \left[ \frac{p(t-t_0) + D}{\sqrt{2p}} \right]^2 - i\pi/4 \right\}, \quad (V-17)$$

where negligible contributions from the last term of (V-16) have been dropped. By use of (V-14), (V-17) can be written as

$$A_n(t) \approx -i \frac{a\sqrt{\pi} \overline{NC}(n)}{(\overline{n\Omega}(r+r'))^{1/2}} \left[ 1 - \frac{r'}{\pi(r+r')} \left( 1 + \frac{\Lambda_0^2}{\omega_0^2 - \overline{n^2\Omega^2}} \right) \right] \\ \times \exp \left\{ i \frac{[\omega_0^2 + \Lambda_0^2 - \overline{n^2\Omega^2} + (r+r')(t-t_0)]^2}{4n\Omega(r+r')} - i \frac{\pi}{4} \right\}. \quad (V-18)$$

## 6. EVALUATION OF BEAM POSITION AND SIZE

We are now in a position to evaluate the local center-of-mass displacement,  $\bar{x}$ , and the rms beam width,  $\delta$ , which were defined in (III-7) and (III-8).

### 6.1. Case a: $\Delta^2/\Lambda_0^2 \ll 1$

Using (IV-16), (IV-17), (V-12), and (V-18), and introducing the quantities

$$\Delta^4 = \frac{1}{N} \sum_{k=0}^{N-1} (\omega_k^2 - \omega_0^2)^2, \quad (VI-1)$$

$$\Delta_1^4 = \frac{1}{N} \sum_{k=0}^{N-1} (\omega_k^2 - \omega_0^2)^2 e^{-2\pi ik/N}, \quad (VI-2)$$

so that  $\Delta^2$  is the rms spread in the square of the frequency shift, one obtains



$$\bar{x} = \frac{a}{\omega_0^2 - (\bar{n}\Omega)^2} - ia \left( \frac{\pi}{\bar{n}\Omega(r+r')} \right)^{1/2} \left[ 1 - \frac{r'}{\pi(r+r')} \left( 1 + \frac{\Lambda_0^2}{\omega_0^2 - \bar{n}^2\Omega^2} \right) \right]$$

$$\times \exp \left\{ i \frac{[\omega_0^2 + \Lambda_0^2 - \bar{n}^2\Omega^2 + (r+r')(t-t_0)]^2}{4\bar{n}\Omega(r+r')} - i \frac{\pi}{4} \right\} \frac{\Delta_1^4}{\Lambda_0^4},$$

(VI-3)

$$\delta^2 = \left\{ a \left( \frac{\pi}{\bar{n}\Omega(r+r')} \right)^{1/2} \left[ 1 - \frac{r'}{\pi(r+r')} \left( 1 + \frac{\Lambda_0^2}{\omega_0^2 - \bar{n}^2\Omega^2} \right) \right] \right\}^2$$

$$\times \left\{ \frac{\Delta_1^4}{\Lambda_0^4} - \frac{|\Delta_1^4|^2}{\Lambda_0^8} \right\}$$

$$- \frac{a}{\omega_0^2 - \bar{n}^2\Omega^2} a \left( \frac{\pi}{\bar{n}\Omega(r+r')} \right)^{1/2} \left[ 1 - \frac{r'}{\pi(r+r')} \left( 1 + \frac{\Lambda_0^2}{\omega_0^2 - \bar{n}^2\Omega^2} \right) \right]$$

$$\times 2 \operatorname{Re} \left\{ \frac{\Delta_1^4}{\Lambda_0^4} \exp \left[ i \frac{[\omega_0^2 + \Lambda_0^2 - \bar{n}^2\Omega^2 + (r+r')(t-t_0)]^2}{4\bar{n}\Omega(r+r')} - i \frac{\pi}{4} - i \frac{\pi}{2} \right] \right\}.$$

(VI-4)

If

$$\left( \frac{\pi}{\bar{n}\Omega(r+r')} \right)^{1/2} \gg \frac{1}{\omega_0^2 - \bar{n}^2\Omega^2},$$

(VI-5)

and

$$\left(\frac{\pi}{n\Omega(r+r')}\right)^{1/2} \frac{\Delta^4}{\Lambda_0^4} \ll \frac{1}{\omega_0^2 - n^2\Omega^2}, \quad (\text{VI-6})$$

then (VI-3) and (VI-4) become

$$\bar{x} \approx \frac{a}{\omega_0^2 - n^2\Omega^2}, \quad (\text{VI-7})$$

$$\delta \approx a \left(\frac{\pi}{n\Omega(r+r')}\right)^{1/2} \frac{\Delta^2}{\Lambda_0^2} \left[ 1 - \frac{r}{\pi(r+r')} \left( 1 + \frac{\Lambda_0^2}{\omega_0^2 - n^2\Omega^2} \right) \right]. \quad (\text{VI-8})$$

Equation (VI-7) shows that, when the rate of change of  $\omega$  and  $\Lambda$  and the frequency spread are such as to satisfy (VI-5) and (VI-6), the local beam center of mass is essentially not influenced by the resonance crossing (but only by the proximity of the coherent integral resonance). However, and under the same conditions, the crossing of the resonance can lead to an increase of beam size, as shown by (VI-8).

It is interesting to compare these results with the increase in amplitude of a single particle crossing the resonance. For a single particle the amplitude after crossing is given by

$$x_s = a \left(\frac{\pi}{n\Omega r}\right)^{1/2}.$$

Taking, for the sake of comparison,  $r' = 0$  the increase in beam size,  $\delta$ , is seen to be equal to  $x_s$  multiplied by the factor  $\Delta^2/\Lambda_0^2$ , i.e., the ratio of frequency spread to frequency shift.

As a numerical example consider the case of an ERA with parameters  $\Omega = 10^{10} \text{ sec}^{-1}$ ,  $R$  (ring radius)  $\approx 3 \text{ cm}$ ,  $\omega_0 - \Omega \approx 2 \times 10^{-2} \Omega$ ,  $r = 2\omega_0 (d\omega_0/dt) \approx 2 \times 10^{24} \text{ sec}^{-3}$ ,  $r' = 0$ ,  $(\Delta/\Lambda) \approx 10^{-1}$ ,  $a = -R\Omega^2 (\Delta B/B) \approx 3 \times 10^{20} (\Delta B/B) \text{ sec}^{-2}$ ,  $\bar{n} = 1$ . The quantity  $r$  corresponds to a case such that  $\omega_0/\Omega$  changes by 0.1 in 10  $\mu\text{sec}$ , a value typical for the ERA. One sees that (VI-5) and (VI-6) are satisfied for these parameters. From (VI-7) and (VI-8) one has

$$\bar{x} \approx 30 (\Delta B/B) \text{ cm},$$

$$\delta \approx 37.5 (\Delta B/B) \text{ cm},$$

so that a value of  $\Delta B/B$  less than  $10^{-3}$  should suffice to keep the effect of the resonance crossing within tolerable limits.

### 6.2. Case b: $\Delta^2/\Lambda_0^2 \gg 1$ .

From (V-10), (IV-21), and (IV-22) and from (III-7) and (III-8), we have

$$\bar{x} = a \left( \frac{\pi}{\bar{n}\Omega(r+r')} \right)^{1/2} \frac{1}{N} \sum_k \exp \left\{ i \left[ \frac{(D_k + p(t-t_0))^2}{2p} \right] \right\} \quad (\text{VI-9})$$

and

$$\delta^2 = \frac{a^2 \pi}{\bar{n}\Omega(r+r')} \left\{ 1 - \frac{1}{N^2} \sum_{k,h} \exp \left[ i \left( \frac{D_k + p(t-t_0)}{\sqrt{2p}} \right)^2 - i \left( \frac{D_h + p(t-t_0)}{\sqrt{2p}} \right)^2 \right] \right\}. \quad (\text{VI-10})$$

Assuming, again, that condition (V-8) is satisfied, (VI-9) and (VI-10) become, to a good approximation,

$$\bar{x} \approx 0, \quad (\text{VI-11})$$

$$\delta \approx a \left\{ \frac{\pi}{n\Omega(r+r')} \right\}^{1/2}. \quad (\text{VI-12})$$

These last results are equivalent to saying that each particle behaves as a single particle, so that, because of the large frequency difference between particles, their center of mass averages to zero and one gets essentially only a beam widening. But the width increase is larger, by a factor of  $k^2/\Lambda_0^2$ , than that obtained in case (a).

#### ACKNOWLEDGMENTS

We are indebted to G. Lambertson, L. Smith, and S. Van der Meer for stimulating conversations and, in particular, to L. Smith who pointed out an error in the original manuscript.

REFERENCES

- \* This work was supported by the U. S. Atomic Energy Commission.
- † Permanent address: Laboratori Nazionali di Frascati, Frascati (Roma), Italy.
- 1) V. P. Sarantsev, Proc. Particle Accelerator Conf., Washington, D. C., IEEE Transactions on Nuclear Science NS-16, #3 (1969), p. 15;  
D. Keefe, Proc. Particle Accelerator Conf., Washington, D. C., IEEE Transactions on Nuclear Science NS-16, #3 (1969), p. 25.
  - 2) A. Garren et al., Nucl. Instr. and Meth. 18-19 (1962) 525.
  - 3) J. D. Lawson, in Symp. on Electron Ring Accelerators held at Lawrence Radiation Laboratory, Berkeley, California, UCRL-18103 (1968), p. 301.
  - 4) K. R. Symon, Nucl. Instr. and Meth. 18-19 (1962) 304.
  - 5) L. J. Laslett, Lawrence Radiation Laboratory, Berkeley, California, ERA internal report, 1969 (unpublished).
  - 6) A. M. Sessler, in Symp. on Electron Ring Accelerators held at Lawrence Radiation Laboratory, Berkeley, California, UCRL-18103 (1968), p. 11.
  - 7) A. G. Bonch-Osmolovskii et al., Joint Institute for Nuclear Research, Dubna, USSR, preprint JINR-PG-4135 (1968).
  - 8) See Ref. 7 and also L. J. Laslett, internal report ERAN-51, Lawrence Radiation Laboratory, Berkeley, California (1970).
  - 9) S. Van der Meer, CERN preprint ISR-PO-169-57 (1969).
  - 10) V. P. Sarantsev et al., in Proc. of the VII Int. Conf. on High Energy Accelerators, Yerevan, USSR (1969), (to be published).

#### LEGAL NOTICE

*This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:*

- A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or*
- B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.*

*As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.*

TECHNICAL INFORMATION DIVISION  
LAWRENCE RADIATION LABORATORY  
UNIVERSITY OF CALIFORNIA  
BERKELEY, CALIFORNIA 94720