Lawrence Berkeley National Laboratory

Recent Work

Title

Amorphous Silicon Position Sensitive Neutron Detector

Permalink

<https://escholarship.org/uc/item/6wz405bc>

Journal

IEEE Transactions on Nuclear Science, 39(4)

Authors

Miresghhi, A.
Cho, G.
Drewery, J.
et al.

Publication Date

1991-10-01

Lawrence Berkeley Laboratory

UNIVERSITY OF CALIFORNIA

Physics Division

Submitted to IEEE Transactions on Nuclear Science

Amorphous Silicon Position Sensitive Neutron Detector

A. Miresghi, G. Cho, J. Drewery, T. Jing, S.N. Kaplan,
V. Perez-Mendez, and D. Wildermuth

October 1991

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. Neither the United States Government nor any agency thereof, nor The Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or The Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or The Regents of the University of California and shall not be used for advertising or product endorsement purposes.

Lawrence Berkeley Laboratory is an equal opportunity employer.

DISCLAIMER

This document was prepared as an account of work sponsored by the United States Government. While this document is believed to contain correct information, neither the United States Government nor any agency thereof, nor the Regents of the University of California, nor any of their employees, makes any warranty, express or implied, or assumes any legal responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by its trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or the Regents of the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof or the Regents of the University of California.

Amorphous Silicon Position Sensitive Neutron Detector

A. Miresghhi*, G. Cho, J. Drewery, T. Jing, S.N. Kaplan, V. Perez-Mendez, D. Wildermuth

Lawrence Berkeley Laboratory, University of California, Berkeley, CA 94720

Abstract

In this work, we present an investigation of the possibility of using a-Si:H diode coated with an appropriate converter, as a position sensitive neutron detector. Our Monte Carlo simulation predicts that using a Gd film $\sim 2\mu\text{m}$ thick, coated on a sufficiently thick amorphous silicon n-i-p diode, we can achieve a neutron detection efficiency of 25 percent. The experimental results presented give an average signal size of about 12000 e^- per neutron interaction, which is well above the noise and is in good agreement with the expected values. We can also fabricate pixel detectors with element size as small as 300 μm and still register a count rate of 2200 events/sec in a typical neutron flux situation of about 10^7 n/cm².sec. The fact that these detectors are not sensitive to gamma rays, and show excellent radiation hardness, make them good candidates for being used in applications such as neutron imaging, neutron crystallography and neutron scattering.

I. INTRODUCTION

The application of a-Si:H diodes as charged particle and X-ray detectors has been previously reported [1]. Moreover, some important characteristics such as, charge collection, signal generation and noise have been studied [2]. In fact, the possibility of laying out a substantial number of small size diode pixels on a large substrate makes a-Si:H an appropriate choice as a Position Sensitive Detector (PSD). By interfacing such arrays with suitable neutron converters, it is possible to develop neutron-sensitive PSD's with desirable spatial resolution and efficiency. An obvious and important application for neutron PSD would be neutron crystallography, and neutron imaging or real-time neutron radiography, a NDT method which has been a typical utilization of research reactors for several decades. The World Conferences in Neutron Radiography, specially the recent ones [3,4,5] have contained many papers on neutron imaging systems. The image capturing part of all neutron imaging systems is a so called neutron camera. Some neutron cameras are just a Thomson tube, an image intensifier tube with an internal neutron

sensitive scintillator screen [6]. Others use a combination of an external scintillating screen optically coupled to a TV camera through a front surface mirror and some lens system, referred to as LTV [7]. A matrix of neutron-sensitive a-Si:H pixels in conjunction with an array of TFT amplifiers and readout electronics (Fig. 1) may be considered as an alternative to neutron cameras with better or comparable spatial resolution and at a much lower cost. In Fig. 1 the pixel readout uses thin film transistors made of a-Si:H. TFT readout fabricated from poly-crystalline silicon can give a faster readout time. Another important area of application of position sensitive neutron detectors is neutron scattering. For this application, various kinds of PSD's with spatial resolution ranging from

(a)

(b)

Fig.1 (a) Schematic diagram of a-Si:H pixel detector,
(b) Structure of a single pixel

This work was supported by the Director, Office of Energy Research, office of High Energy and Nuclear Physics, Division of High Energy Physics, and Office of Health and Environmental Research, Division of Physics and Technological Research of the U.S. Department of Energy under contract No. DE-AC03-76SF00098.

* Visiting Scholar at LBL from Sharif University of Technology, Tehran, Iran.

0.5 to a few mm, such as: proportional-counters, Microchannel-plates, and Anger cameras have been used [8]. For this specific application, in which good fast neutron and gamma rejection is a desirable requirement, the a-Si:H based PSD offers advantages over the currently used detector configurations. The radiation hardness property of a-Si:H neutron detectors together with the possibility of being fabricated in small sizes, make them suitable for direct beam measurements as well.

In the following we will review different kinds of available neutron converters, and give the results of our Monte Carlo simulation of a Gd neutron converter. This analysis suggest that using a Gd film $\sim 2 \mu\text{m}$ on a fairly thick amorphous Si diode ($30 \mu\text{m}$), we can detect thermal neutrons with an efficiency of 25 percent. Our experimental results are presented and their agreement with the Monte Carlo analysis is discussed.

II. DETECTOR

A. Neutron Converter

The neutron converter material used with a-Si:H diodes arrays should be either provided in the form of a screen in close proximity to it, or coated as a thin layer on the top contact of the planar device. Commonly used neutron converter materials are Boron (^{10}B), Lithium (^6Li), and Gadolinium (Gd). The first two produce alpha particles with energies close to 2 MeV, but the range of these alpha particles in the converter itself are much less than the mean free path of thermal neutrons, resulting in low detection efficiency. A simple calculation shows that for pure ^{10}B and ^6Li films the converter efficiencies (escaping α particle per neutron) are limited to 5 and 2 percent, respectively. However, for Gd even in the natural isotopic mixture, our Monte Carlo simulation (see next section) predicts an efficiency as high as 25 percent. Gd foils have a history of being used in neutron radiography in

Fig. 2 Variation of Gd₂O₂S spatial resolution with thickness

conjunction with X-ray films, but not in real time applications (such as neutron imaging). Gd has a very high cross section for thermal neutron capture, which yields short range conversion electrons of about 70 KeV energy. These have a mean range of about $25 \mu\text{m}$ in silicon; the energy deposition of these low energy electrons will be very localized and therefore, a high spatial resolution can be achieved. All these advantages plus the fact that we are able to coat fairly thick films of this metal on a-Si:H samples, make the Gd the best converter. There are several commercial neutron sensitive scintillators commonly used in real time neutron radiography. The one frequently used is a composite screen of ZnS(Ag), ^6LiF called NE426. The other one named Trimax2 is a Gd₂O₂S:Tb compound used in Thomson tubes. The spatial resolution of the commercially available Gd₂O₂S is appreciably higher than NE426. Hitachi co. has also produced a ceramic scintillator made of Gd₂O₂S:Pr,Ce,F... compacted by hot isostatic processing [9], which has been shown to have good properties for X-ray detection. All of these neutron sensitive scintillators have the drawback of containing high Z elements and therefore being gamma sensitive. This is of course, an undesirable feature for applications where neutron beams contain appreciable gamma fluxes. We have considered using Hitachi Gadolinium Oxysulfate scintillators for our purpose. The result of our calculation, based on a semi Monte-Carlo analysis of point spread function (Fig. 2), indicates that with layers as thick as 0.3 mm, a FWHM resolution of 0.5 mm is achievable. This figure shows an improvement over the microchannel plates, currently used as high resolution devices in neutron scattering [8]. Meanwhile we have measured the light producing efficiency of several 1.1 mm Hitachi samples to be about 28000 to 30000 electron-hole pairs per 1 MeV of deposited energy. This number suggests a signal size of about 2000 e^- from the 70 KeV electron, produced by neutron capture on Gd content of the scintillator, which is not much above the expected noise. On the other hand, in our effort to detect the thermalized neutrons from a 70 Ci Pu-Be source, by a p-i-n diode covered with one of these samples, we found that the Gd₂O₂S scintillator is quite sensitive to source gamma rays. From this finding and also by considering the small signal predicted, we concluded that the use of this scintillator could not serve our purpose.

B. Monte Carlo Simulation

Monte Carlo Analysis was used to simulate the interaction of incident thermal neutrons with a Gd converter and subsequent energy loss of the resulting conversion electrons. Due to the large neutron capture cross sections of the predominant Gd isotopes (^{155}Gd and ^{157}Gd), other reactions were assumed to have negligible effect. An investigation of all possible conversion electron lines for both isotopes, provided in detail, the energies and emission probabilities of all electrons. Because of the relatively low energies of the conversion electrons (average energy $\sim 70 \text{ KeV}$), calculation of their energy loss was done by using the

range-energy relation to find the residual range, and from that

(a)

(b)

(c)

Fig. 3 Monte Carlo simulation results; (a) neutron stopping and event efficiency, (b) simulated pulse height distribution for two different Gd film thicknesses, (c) variation of average signal size with Gd film thickness

the energies of electrons escaping the Gd film and entering the a-Si:H detector were found. The angular distribution of electrons at their points of creation were assumed to be isotropic. Neutron stopping and conversion electron efficiencies as a function of Gd film thickness are shown in Fig. 3.a. Electron events are defined to be: "those neutron captures involving internal conversion electron emission (rather than γ emission), from which at least one of the electrons would be able to escape the Gd film into the amorphous silicon diodes". The neutron stopping efficiency increases and saturates at about three times the mean free path. But the electron event efficiency passes through a maximum of 25 percent at film thickness of about 4 μm . The decline afterwards is due to the fact that, for a given film thickness, most of the neutrons are stopped in lower depths and therefore, the chance of electrons escaping the film will decrease as the thickness increases. In Fig. 3.b we show the simulated pulse height distribution for two different film thicknesses. The signal size is calculated from the escaping energy of the conversion electrons, assuming: a) the p-i-n diode is sufficiently thick to stop all electrons; b) the average energy required to produce an e-h pair (w) for a-Si:H diode is 4.8 eV [10]. As we can see, for thick Gd films a larger number of conversion electrons, especially the lower energy ones are lost by stopping in the foil. It is also interesting to study the effect of film thickness on the average signal size (Fig. 3.c). For an ideal charge collection by the a-Si:H diode, the minimum occurs at the mean range corresponding to the average energy electrons ($\sim 6 \mu\text{m}$). For thinner films, the number of escaping electrons does not change as much but their energies increase. While for thicker films, only higher energy electrons can escape, resulting in a rise of the average signal size. However, this rise can not continue for very thick films that are able to stop all produced electrons. Our simulation results suggest that a foil thickness of 2 μm , while not being far from optimum event efficiency, would produce the largest average signal in the detector.

Fig. 4 Noise and I-V characteristics of an a-Si:H diode

C. Amorphous Silicon Diode

The internal conversion electrons escaping the Gd layer are detected by an amorphous silicon n-i-p diode. The incoming electrons produce electron-hole pairs by direct interaction in the depleted region of the reversed bias diode. In order for a complete energy deposition, the intrinsic layer should have a thickness larger or, at least comparable to the mean range of the conversion electrons. Therefore, in our experiments we have used diodes with thickness within the range of 25-30 μm , with capacitance values between 50-80 pf. The I-V and noise characteristics of a reversed biased, 27 μm thick n-i-p diode are shown in Fig. 4. The flat portion of the noise at lower voltages comes from the preamplifier loaded with detector capacitance, and to some extent is due to contact and p-layer resistance (Nyquist noise). At higher bias voltages, the shot noise and 1/f contribution show up. The overall noise is proportional to the contact area [11]. With DC bias, the electric field distribution through the intrinsic layer is dependent both on dangling bond density (N_d) and the external bias. In Fig. 5.a we show the bias dependence of the field distribution in a 28 μm thick p-i-n diode. The full depletion is expected to occur at about 500 V. This bias voltage is necessary if a complete collection of produced electron-hole pairs is to take place. However, the extent of charge collection also depends on the shaping time of the amplifier. Fig. 5.b shows that for detector bias that we have used, maximum charge collection efficiency is not possible, for timings faster than 3.5 μsec . In Fig. 5.c we show the charge collection efficiency versus bias voltage for a fixed 3.5 μsec shaping time.

One interesting aspect of a-Si:H pertinent to high dose applications is considered to be its radiation hardness. Radiation damage induced by ~ 1 MeV neutrons up to fluences of $\sim 5 \times 10^{14}$ neutron/cm², measured by the increase in leakage current and in shot noise, were minimal and almost completely disappeared after annealing for 2 hours at $\sim 200^\circ\text{C}$ [1]. In another study [12] photodiode a-Si:H sensors were shown to suffer less than 3 percent change in output signal, over the course of irradiation with a ^{60}Co source to a total dose of $\sim 10^6$ rad.

III. EXPERIMENT

A. Setup

The setup of our experiment is shown in Fig. 6. The peaking time of the CR-(RC)² shaping amplifier used was about 3.5 μsec . The PHA spectra were received by and processed on a microcomputer. The samples were amorphous silicon n-i-p diodes with 4-6 mm diameter metallic top contacts, later covered with 12.5 μm Gd foil or plated with Gd. The Gd coating procedure developed can successfully make uniform and stable films of up to 7 μm thick, over the desired area, while maintaining the required low temperature for prevention of any damage to the sample. Using photo-

lithographic technique to make patterns, and etching Gd with Hydrochloric Acid, we can produce arrays of numerous small

Fig.5 (a) Bias dependence of the internal electric field in 28 μm a-Si:H diode, (b) variation of charge collection efficiency with shaping time, (c) bias dependence of the charge collection efficiency

Fig. 6 Bloch diagram of the experimental setup

size detectors for our future imaging tests.

Thermal neutrons were produced by moderating neutrons from a 70 Ci Pu-Be source in a special water hole arranged in a concrete floor. At the detector location the thermal flux was about $400 \text{ n/cm}^2\cdot\text{sec}$, a value which is extremely low compared to the minimum neutron flux $\sim 10^4 \text{ n/cm}^2/\text{sec}$, used in any neutron radiography application.

B. Results and Discussion

The spectrum of events related to neutrons detected by a $20 \mu\text{m}$ thick n-i-p diode, coated with $5 \mu\text{m}$ Gd with an effective area of $\sim 0.1 \text{ cm}^2$ is shown in Fig. 7.a. A reverse bias of 250V was applied, and a net count rate of $\sim 9 \text{ events/sec}$ was recorded. Due to a high noise level in our system electronics, signals below 10000 e^- , overwhelmed by noise, were eliminated by raising the PHA threshold. The mean signal size is $\sim 11900 e^-$, which considering an approximately 77 % charge collection efficiency of the diode for the applied bias and shaping time (Fig. 5.c), is only 7% higher than the estimated value by the Monte Carlo simulation results of Fig. 3.c This difference would have been removed if the smaller size signal had not been lost by the hreshold setting. The background subtracted spectra for two amorphous silicon n-i-p diodes covered with 5 and $12.5 \mu\text{m}$ Gd films are shown in Fig. 7.b The spectrum for the detector with the thinner converter, has about 2 times more counts compared to the other one. This is consistent with the expected event efficiencies calculated by our Monte Carlo analysis (Fig. 3.a). The data related to the mean signal

expected average signal size is again the missing contribution of the lower part of the spectra. For the $20 \mu\text{m}$ diode, which is thinner than the mean range of the average energy conversion electron, some signal loss due to this effect might have compensated for the greater cut in the low level signals resulting in an smaller difference.

loss due to this effect might have compensated for the greater cut in the low level signals resulting in an smaller difference.

We have also measured the gamma sensitivity of the $28 \mu\text{m}$ sample with the $12.5 \mu\text{m}$ Gd foil, by a 10 minute exposure to a 105 mCi Ra source. The net number of count was 440, giving a near zero sensitivity of .001 percent.

Fig. 7 Experimental results; (a) pulse height distribution of $25 \mu\text{m}$ diode covered with $5 \mu\text{m}$ Gd, (b) comparison of results for two different thicknesses of Gd film used

IV. CONCLUSION

In our investigation of the use of a-Si:H diodes for neutron detection, we found that with adequately thick n-i-p diodes coated with $\sim 2 \mu\text{m}$ Gd film, one can detect thermal neutrons

Table-I
Comparison of expected and measured average signal size

Characteristics	Diode #1 ($28 \mu\text{m}$)	Diode #2 ($20 \mu\text{m}$)
Convertor thickness (μm)	12.5	5
Diode charge collection efficiency	%43	%77
Expected signal size (e^-)	6320	11200
Average measured signal size (e^-)	7350	11890

size for both detectors is presented in Table-I. In the table the expected signal size is taken from Fig. 3.c, and then multiplied by the respective charge collection efficiencies of the diodes. The reason for the discrepancy between the measured and

with an efficiency of about 25%. This means that a pixel size of $0.3 \times 0.3 \text{ mm}^2$, in a flux of $10^7 \text{ n/cm}^2 \cdot \text{sec}$ which is a typical flux used in most applications, including neutron imaging, will register more than 2200 events/sec. Considering the other favorable properties of these detectors, such as radiation hardness and insensitivity to gamma rays, that we have shown, the a-Si:H seems to be an excellent candidate for a neutron position sensitive detector.

Acknowledgement

We would like to thank T.R. Corbin and R. Zavala from Environmental Health and safety Group of LBL for making the neutron source available, and R. Hollingsworth from the Material Research Group for providing thick n-i-p diodes.

V. REFERENCES

- [1] V. Perez-Mendez, G. Cho, I. Fujieda, S. N. Kaplan, S. Qureshi, "The application of thick hydrogenated amorphous silicon layers to charged particle and x-ray detectors," *Mat. Res. Soc. Symp. Proc.* vol. 149, pp. 621-630, 1988.
- [2] S. Qureshi, V. Perez-Mendez, S.N. Kaplan, I. Fujieda, G. Cho, "Signal generation in a hydrogenated amorphous silicon detector," *IEEE Trans. Nuc. Sci.* vol. 36, pp. 194-198, 1989.
- [3] J.P. Barton and P. von der Hardt, eds., *Proc. 1st World Conf. on Neutron Radiography*, San Diego, California, Dec. 1981, Kluwer Boston 1983.
- [4] J.P. Barton, G. Farny, J.L. Person and H. Rottger, eds., *Proc. 2nd World Conf. on Neutron Radiography*, Paris, France, June 1986, Kluwer Academic, 1987.
- [5] Shigenori Fujine, ...eds., *Proc. 3rd World Conf. on Neutron Radiography*, Osaka, Japan, May 1989, Kluwer Academic 1990.
- [6] V. Orphan, D. Kedem, F. Johansen, "Mobile neutron radiography system for aircraft inspection," *Proc. 2nd World Conf. on Neutron Radiography*, Paris, France, June 1986, Kluwer Academic, 1987, pp. 447-454.
- [7] W.E. Dance and S.F. Carollo, "High sensitivity Electronic imaging system for reactor or non-reactor neutron radiography," *Proc. 2nd World Conf. on Neutron Radiography*, Paris, France, June 1986, Kluwer Academic, 1987, pp. 415-422.
- [8] R.K. Crawford, J.R. Haumann, J.E. Epperson, P. Thiagarajan, A.J. Schultz, G.P. Felcher, D. G. Montague and R.J. Dejus, "Experience with position sensitive neutron detectors at the intense pulsed neutron source," *Nucl. Instr. and Meth.* A299, pp. 17-24, 1990.
- [9] Yukio Ito, Hiromichi Yamada, Minoru Yoshida, Hideji Fujii, Hiroshi Takeuchi and Yasuo Tsukuda, "Hot isostatic pressed Gd₂O₃:Pr,Ce, F translucent scintillator ceramics for x-ray computed tomography detectors," *Japanese Journal of Applied Physics*, Vol. 27, pp. L1371-L1373, 1988.
- [10] V. Perez-Mendez, chapter 8 in "Physics and applications of amorphous and microcrystalline semiconductor devices," J. Kanicki, ed., Boston, MA., Artech House Pub., 1991, pp. 297-330.
- [11] G. Cho, J. drewery, I. Fujieda, S.N. Kaplan, V. Perez-Mendez, S. Qureshi, "Measurement of 1/f noise in a a-Si:H pin diode and thin-film-transistor," *Mat. Res. Soc. Symp. Proc.* vol. 192, 1990, pp. 393-398.
- [12] L.E. Antonuk, J. Boudry, J. Yorkston and C.F. Wild, "Radiation damage studies of amorphous silicon photodiode sensors for applications in radiotherapy x-ray imaging," *Nucl. Instr. and Meth.*, A299, pp. 143-146, 1990.

LAWRENCE BERKELEY LABORATORY
UNIVERSITY OF CALIFORNIA
INFORMATION RESOURCES DEPARTMENT
BERKELEY, CALIFORNIA 94720