UC Merced UC Merced Previously Published Works

Title

Regional gradient controllability of ultra-slow diffusions involving the Hadamard-Caputo time fractional derivative

Permalink https://escholarship.org/uc/item/49x1m5tt

Journal Mathematical Control and Related Fields, 10(1)

ISSN 2156-8472

Authors

Cai, Ruiyang Ge, Fudong Chen, Yangquan <u>et al.</u>

Publication Date 2020

DOI

10.3934/mcrf.2019033

Peer reviewed

REGIONAL GRADIENT CONTROLLABILITY OF ULTRA-SLOW DIFFUSIONS INVOLVING THE HADAMARD-CAPUTO TIME FRACTIONAL DERIVATIVE

RUIYANG CAI

College of Information Science and Technology, Donghua University Shanghai 201620, China

Fudong Ge*

School of Computer Science, China University of Geosciences Wuhan 430074. China

YANGQUAN CHEN

School of Engineering (MESA-Lab), University of California Merced, CA 95343, USA

Chunhai Kou

Department of Applied Mathematics, Donghua University Shanghai 201620, China

(Communicated by Qi Lü)

ABSTRACT. This paper investigates the regional gradient controllability for ultra-slow diffusion processes governed by the time fractional diffusion systems with a Hadamard-Caputo time fractional derivative. Some necessary and sufficient conditions on regional gradient exact and approximate controllability are first given and proved in detail. Secondly, we propose an approach on how to calculate the minimum number of ω -strategic actuators. Moreover, the existence, uniqueness and the concrete form of the optimal controller for the system under consideration are presented by employing the Hilbert Uniqueness Method (HUM) among all the admissible ones. Finally, we illustrate our results by an interesting example.

1. Introduction. In recent years, fractional differential equations have attracted increasing interests and a wide number of monographs have been published both in its basic theory and applications (see e.g. the monographs [8, 22, 32, 35] and the references cited therein). In particular, the introduction of the continuous time random walk (CTRW) theory, which is closely related to the anomalous diffusion [1, 38], sets off a new wave in the research on fractional order systems, whose unique power-law property efficiently describes the characteristics of the anomalous diffusion. Nevertheless, most of these studies on anomalous diffusion are involved in

²⁰¹⁰ Mathematics Subject Classification. Primary: 93B05, 35R11; Secondary: 60J60.

Key words and phrases. Ultra-slow diffusion processes, regional gradient controllability, Hadamard-Caputo time fractional derivative, Hilbert Uniqueness Method.

The second author is supported by the Fundamental Research Funds for the Central Universities, China University of Geosciences, Wuhan (No.CUG170627), the Natural Science Foundation of China (NSFC, No.KZ18W30084) and the Hubei NSFC (No.2017CFB279).

Corresponding author.

Riemann-Liouville and Caputo fractional derivatives, while the Hadamard fractional derivative, which was introduced in 1892 [16], has not been researched so much as the previous two even though it has some special features. The main differences between the Hadamard fractional derivative and the above two common kinds of fractional derivative focus on two aspects. On one hand, the Hadamard fractional derivative involves an integral kernel of logarithmic function with an arbitrary exponent, which could be more effective in describing the ultra-slow diffusion processes. On the other hand, the $t\frac{d}{dt}$ in its definition has shown to be invariant on the half-axis in concerns of dilation [13]. For more knowledge of the Hadamard fractional integral and derivative, we refer the reader to [5, 23].

The applications of the Hadamard fractional derivative are also abundant in real world. For example, fractional thermoelasticity [33], kinetic theory of gases [37] and physical phenomena in fluctuating environments [36], which are special cases of ultra-slow diffusion processes. The Hadamard fractional derivative can well describe these situations because of the ultra-slow increasing rate of log t compared with t (t > 0), while both Riemann-Liouville and Caputo fractional derivatives cannot meet these needs.

Nowadays, several theoretical results on Hadamard fractional differential equations have been obtained. Two surveys [2, 27] proved the existence of solutions and weak solutions for some classes of Hadamard type fractional differential equations with and without impulse effects and presented the analytical solutions in terms of the Mittag-Leffler function. The authors in [4] investigated the initial and boundary value problems of Hadamard fractional differential equations and inclusions, and obtained some new results on them. The asymptotic behavior of solutions of nonlinear Caputo-type Hadamard fractional differential equations was established in [15]. More contributions in this field can be found in [7, 18, 19]. However, the studies on the controllability theory and applications of Hadamard time fractional diffusion systems are still on their early stages and need further investigation, even though there are a great many works on the controllability of diffusion systems [20, 21, 24], and fractional systems [14, 31].

Notice that in practical applications not all the diffusion systems can be controlled on the whole domain. Hence, regional controllability should be considered, where we concern the systems under consideration only within some subregions of the whole domain [3, 8]. We claim, in addition, that the concept of regional gradient controllability makes sense in many real-life applications. One of the most important applications is in forest fire. Other than put out the fire directly, fire fighters usually try to control its spread, namely the gradient of fire intensity. Other applications can be found in thermic isolation problem, industrial ceramics, etc. By considering the characteristics of actuators, our goal here is to study the regional gradient controllability of the Hadamard time fractional diffusion systems, which is suitable for a much wider range of physical phenomena. This is especially appealing for these systems which are not gradient controllable on the whole domain. Furthermore, it is worth mentioning that a number of remarkable new results have been derived by Zerrik et al. [39, 40, 41] on the regional gradient controllability of integer order diffusion systems. Nowadays, the authors in [9, 10, 11] have extended to study the regional (gradient) controllability of time fractional diffusion systems with the Riemann-Liouville and the Caputo fractional derivatives. Besides, we note that the initial condition of the Caputo fractional differential equation is the same as that of integer order, which has a more intuitive physical interpretation and easier to realize in engineering. With these, in this paper, we will adopt the Caputo type modification of the Hadamard fractional derivative, the so called Hadamard-Caputo fractional derivative, introduced in [18], to establish some criteria for the regional gradient controllability of Hadamard-Caputo time fractional diffusion systems.

Motivated by the arguments above, herein, we consider the following time fractional diffusion system with a Hadamard-Caputo time fractional derivative:

$$\begin{cases} {}^{HC}_{a} D^{\alpha}_{t} z(x,t) = A z(x,t) + B u(t) \text{ in } \Upsilon, \\ z(x,a) = z_{0}(x) \text{ in } \Omega, \\ z(\xi,t) = 0 \text{ on } \partial\Omega \times [a,b], \end{cases}$$
(1)

where $\Upsilon = \Omega \times [a, b], a > 0, 0 < \alpha < 1, \Omega$ is a bounded open set of \mathbb{R}^n with smooth boundary $\partial\Omega$ and $z(x, \cdot) \in AC[a, b] \triangleq \{z(x, \cdot) : [a, b] \to \mathbb{R} \text{ and } z(x, \cdot) \text{ is absolutely}$ continuous in $[a, b]\}$. Here, A is the infinitesimal generator of a C_0 -semigroup $\{T(t)\}$ on $L^2(\Omega)$ and -A is a uniformly elliptic operator. Besides, $z_0 \in H_0^1(\Omega), u$: $[a, b] \to \mathbb{R}^m$ and $B : \mathbb{R}^m \to H_0^1(\Omega)$ is a bounded linear operator. In addition, ${}_a^{HC}D_t^{\alpha}$ denotes the Hadamard-Caputo time fractional derivative to be specified later. To the best of our knowledge, no results are available on this topic and we hope that the obtained results could provide some insights into the control theory of Hadamard time fractional diffusion systems.

The rest of this paper is organized as follows. Some needed definitions and lemmas are presented in the next section. In Section 3, we give our main results, where the necessary and sufficient conditions on regional gradient exact and approximate controllability for the system (1) are first explored and then we discuss the existence, uniqueness and the concrete form of the optimal controller for the system under consideration. An example is finally worked out to confirm the effectiveness of our results.

2. **Preliminary results.** In this section, we recall some basic definitions and lemmas to be applied throughout this paper.

Definition 2.1. [18] The left-sided and right-sided Hadamard fractional integral of order $\alpha \in \mathbb{C}$, $Re(\alpha) > 0$ of a function f(t) are respectively, defined by

$${}_{a}^{H}I_{t}^{\alpha}f(t) \triangleq \frac{1}{\Gamma(\alpha)} \int_{a}^{t} \left(\log\frac{t}{s}\right)^{\alpha-1} f(s)\frac{ds}{s}$$
(2)

and

$${}^{H}_{t}I^{\alpha}_{b}f(t) \triangleq \frac{1}{\Gamma(\alpha)} \int_{t}^{b} \left(\log \frac{s}{t}\right)^{\alpha-1} f(s)\frac{ds}{s}, \tag{3}$$

where $Re(\alpha)$ denotes the real part of α .

Definition 2.2. [18] Let $Re(\alpha) \geq 0$ and $n = [Re(\alpha)] + 1$. If $f(t) \in AC_{\delta}^{n}[a, b]$, where $0 < a < b < \infty$ and $AC_{\delta}^{n}[a, b] = \{f(t) : [a, b] \to \mathbb{C} \mid \delta^{n-1}f(t) \in AC[a, b], \delta = t\frac{d}{dt}\}$. Define the left-sided and right-sided Hadamard-Caputo fractional derivatives respectively, as follows:

$${}_{a}^{HC}D_{t}^{\alpha}f(t) \triangleq_{a}^{H}D_{t}^{\alpha}\left[f(t) - \sum_{k=0}^{n-1}\frac{\delta^{k}f(a)}{k!}\left(\log\frac{t}{a}\right)^{k}\right]$$
(4)

and

$${}_{t}^{HC}D_{b}^{\alpha}f(t) \triangleq_{t}^{H}D_{b}^{\alpha}\left[f(t) - \sum_{k=0}^{n-1}\frac{(-\delta)^{k}f(b)}{k!}\left(\log\frac{b}{t}\right)^{k}\right],$$
(5)

where ${}_{a}^{H}D_{t}^{\alpha}f(t)$ and ${}_{t}^{H}D_{b}^{\alpha}f(t)$ are the left-sided and right-sided Hadamard fractional derivative, defined by

$${}_{a}^{H}D_{t}^{\alpha}f(t) \triangleq \frac{1}{\Gamma(n-\alpha)} \,\delta^{n} \int_{a}^{t} \left(\log\frac{t}{s}\right)^{n-\alpha-1} f(s)\frac{ds}{s} \tag{6}$$

and

$${}^{H}_{t} D^{\alpha}_{b} f(t) \triangleq \frac{(-1)^{n}}{\Gamma(n-\alpha)} \,\delta^{n} \int_{t}^{b} \left(\log \frac{s}{t}\right)^{n-\alpha-1} f(s) \frac{ds}{s},\tag{7}$$

respectively. In particular, if $0 < Re(\alpha) < 1$ and $f(t) \in AC[a, b]$, where $0 < a < b < \infty$. Then $\frac{HC}{a}D_t^{\alpha}f(t)$ exists everywhere on [a, b] and can be presented by

$${}_{a}^{HC}D_{t}^{\alpha}f(t) = \frac{1}{\Gamma(1-\alpha)}\int_{a}^{t}\left(\log\frac{t}{s}\right)^{-\alpha}f'(s)ds.$$
(8)

Let $\nabla : H_0^1(\Omega) \to (L^2(\Omega))^n$ be the gradient operator defined by

$$\nabla z \triangleq \left(\frac{\partial z}{\partial x_1}, \dots, \frac{\partial z}{\partial x_n}\right)$$

According to the Eq.(2) in [41], then $\nabla^* : (L^2(\Omega))^n \to H^{-1}(\Omega), z \mapsto h$, the adjoint operator of ∇ , can be given by the unique solution of

$$\begin{cases} \Delta h = -div z & in \ \Omega, \\ h = 0 & on \ \partial\Omega. \end{cases}$$
(9)

With this, we give the following definitions.

Definition 2.3. [40] System (1) is said to be regionally gradient exactly (approximately) controllable on ω at time b, if for every $f(x) \in (L^2(\omega))^n$ and any $\varepsilon > 0$, there exists a $u \in L^2([a, b], \mathbb{R}^m)$ such that

$$p_{\omega} \nabla z_u(x,b) = f(x) \left(\parallel p_{\omega} \nabla z_u(x,b) - f(x) \parallel_{(L^2(\omega))^n} < \varepsilon \right),$$
(10)

where p_{ω} is the restriction map from Ω to its subset ω .

Remark 1. In Definition 2.3, if we choose $\omega = \Omega$, then the definition of regional controllability coincides with that of the classical controllability.

Definition 2.4. [39] The actuator (actuators) is (are) said to be gradient ω -strategic if system (1) is regionally gradient approximately controllable on ω at time b.

To discuss the regional controllability problem of system (1), the following generalized Mittag-Leffler function of two parameters [22] is needed:

$$E_{\alpha,\beta}(z) \triangleq \sum_{n=0}^{\infty} \frac{z^n}{\Gamma(n\alpha+\beta)},$$

where $z \in \mathbb{C}$, $Re(\alpha) > 0$. We see that when $\beta = 1$, $E_{\alpha,\beta}(z) = E_{\alpha}(z)$, the Mittag-Leffler function in one parameter. For $\alpha = 1$, we have $E_1(z) = e^z$, which is the exponential function.

Based on the Theorem 3.6 and 3.8 in [27], we present two important lemmas as follows.

5

Lemma 2.5. Let $0 < \alpha < 1$. If there exists constants $k > -\alpha$, $l \leq 0$ with $l > \max\{-\alpha, -\alpha - k\}$ and $M \ge 0$ such that $||Bu(t)|| \le Mt^k(1-t)^l$ for all $t \in (a, b)$. Then system (1) has a unique solution

$$z(x,t) = S_{\alpha} \left(\log \frac{t}{a} \right) z_0(x) + \int_a^t \left(\log \frac{t}{s} \right)^{\alpha - 1} K_{\alpha} \left(\log \frac{t}{s} \right) Bu(s) \frac{ds}{s},$$

where

$$S_{\alpha}(t) = \int_{0}^{\infty} \phi_{\alpha}(s) T(t^{\alpha}s) \, ds$$

and

$$K_{\alpha}(t) = \alpha \int_{0}^{\infty} s\phi_{\alpha}(s)T(t^{\alpha}s) \, ds.$$

Here,
$$\phi_{\alpha}(s) = \frac{s^{-\frac{1}{\alpha}-1}}{\alpha} \eta_{\alpha} \left(s^{-\frac{1}{\alpha}}\right)$$
 and $\eta_{\alpha}(s)$ is defined by

$$\eta_{\alpha}(s) = -\sum_{n=1}^{\infty} \frac{\Gamma(n\alpha+1)}{n!\pi s} \left(\frac{-1}{s^{\alpha}}\right)^n \sin n\pi\alpha, s \in (0,\infty).$$

Proof. Because of the equivalence between $\|\cdot\|_{L^1}$ and $\|\cdot\|_{L^2}$ in a bounded domain, thus, $u(t) \in L^2([a, b], \mathbb{R}^m)$ is bounded. This, together with that B is a bounded linear operator, yields that we can choose k = l = 0 such that for some M > 0, $|| Bu(t) || \le || B || || u || \le M$ to satisfy the assumption in this lemma.

We choose the Picard function sequence as $\eta_0(x,t) = z_0(x)$ and

$$\eta_i(x,t) = z_0(x) + \frac{1}{\Gamma(\alpha)} \int_a^t \left(\log\frac{t}{s}\right)^{\alpha-1} \left(A\eta_{i-1}(x,s) + Bu(s)\right) \frac{ds}{s},$$

for $x \in \Omega$, $t \in [a, b]$ and $i = 1, 2, \cdots$. Similar to Claim 1~3 in [27], we can prove that

(i) $\eta_i(x,t) \in C(\Omega \times [a,b]), i = 1, 2, \cdots;$

(ii) $\{\eta_i(x,t)\}_{n\geq 1}$ converges uniformly to $\eta(x,t)$ with $(x,t) \in \Omega \times [a,b]$;

(iii) $\eta(x,t) = \lim_{i \to \infty} \eta_i(x,t)$ is the unique continuous solution of the Picard function sequence given by

$$\eta(x,t) = z_0(x) + \frac{1}{\Gamma(\alpha)} \int_a^t \left(\log\frac{t}{s}\right)^{\alpha-1} \left(A\eta(x,s) + Bu(s)\right) \frac{ds}{s}.$$

Moreover, by applying the same iteration procedure as that in Theorem 3.8 of [27], it yields that

$$\eta_i(x,t) = z_0(x) \sum_{k=0}^{i} \frac{A^k \left(\log \frac{t}{a}\right)^{k\alpha}}{\Gamma(k\alpha+1)} + \frac{1}{\Gamma(\alpha)} \int_a^t \left(\log \frac{t}{s}\right)^{\alpha-1} \mu_i(s) Bu(s) \frac{ds}{s}$$
$$\to S_\alpha \left(\log \frac{t}{a}\right) z_0(x) + \int_a^t \left(\log \frac{t}{s}\right)^{\alpha-1} K_\alpha \left(\log \frac{t}{s}\right) Bu(s) \frac{ds}{s}$$
$$\to \infty, \text{ where } \mu_i(s) = \sum_{l=0}^{i} \frac{A^k (\log \frac{t}{s})^{k\alpha}}{\Gamma((k+1)\alpha)}.$$

as ik=0

Remark 2. For the abstract operators A and B involved in system (1), the last formula is given in terms of the operator $S_{\alpha}(t)$ and $K_{\alpha}(t)$, because of the uniqueness of the solution for a linear system (see e.g. [22] or the Theorem 3.8 of [27]). Moreover, the uniqueness of the solution shows that when A is a real number, $S_{\alpha}(t) = E_{\alpha}(At^{\alpha}), K_{\alpha}(t) = E_{\alpha,\alpha}(At^{\alpha})$ and the solution coincides with that in [27].

For more arguments and properties of $S_{\alpha}(t)$, $K_{\alpha}(t)$, $\phi_{\alpha}(t)$ and $\eta_{\alpha}(t)$, we refer the reader to [29, 30, 42].

Lemma 2.6. Let $0 < \alpha < 1$. Then the following problem

$$\begin{cases} {}^{H}_{a}D^{\alpha}_{t}z(x,t) = Az(x,t) \text{ in } \Upsilon,\\ \lim_{t \to a} {}^{H}_{a}D^{\alpha-1}_{t}z(x,t) = z_{0}(x) \text{ in } \Omega,\\ z(\xi,t) = 0 \text{ on } \partial\Omega \times [a,b] \end{cases}$$

has a unique solution satisfying

$$z(x,t) = \left(\log\frac{t}{a}\right)^{\alpha-1} K_{\alpha}\left(\log\frac{t}{s}\right) z_0(x).$$

The proof is similar to that of Lemma 2.5 and we omit it.

Lemma 2.7. [6] Let $\Omega \subseteq \mathbb{R}^n$ be a bounded open set and $C_0^{\infty}(\Omega)$ be the set of infinitely differentiable functions on Ω with compact support. If for $v_1 \in L^1(\Omega)$, such that

$$\int_{\Omega} v_1(x)v_2(x)dx = 0, \quad \forall v_2 \in C_0^{\infty}(\Omega).$$

Then $v_1 = 0$, a.e. in Ω .

Lemma 2.8. Define Q as $Qf(t) = f\left(\frac{ab}{t}\right)$ and assume $0 < \alpha < 1$. Then we have the following equalities:

(i)
$$Q_a^H I_t^{\alpha} f(t) =_t^H I_b^{\alpha} Q f(t)$$
, (ii) $Q_a^H D_t^{\alpha} f(t) =_t^H D_b^{\alpha} Q f(t)$,
(iii) $_a^H I_t^{\alpha} Q f(t) = Q_t^H I_b^{\alpha} f(t)$, (iv) $_a^H D_t^{\alpha} Q f(t) = Q_t^H D_b^{\alpha} f(t)$.

Proof. (i) From Definition 2.1, we have

(iv) It follows from (6) that

$${}^{H}_{a} D^{\alpha}_{t} Q f(t) = {}^{H}_{a} D^{\alpha}_{t} f\left(\frac{ab}{t}\right)$$
$$= \frac{t}{\Gamma(1-\alpha)} \frac{d}{dt} \int_{a}^{t} \left(\log \frac{t}{s}\right)^{-\alpha} f\left(\frac{ab}{s}\right) \frac{ds}{s}$$
$$= \frac{t}{\Gamma(1-\alpha)} \frac{d}{dt} \int_{\frac{ab}{t}}^{b} \left(\log \frac{ut}{ab}\right)^{-\alpha} f(u) \frac{du}{u}.$$

On the other hand,

$$Q\left({}_{t}^{H}D_{b}^{\alpha}f(t)\right) = Q\left(\frac{-t}{\Gamma(1-\alpha)}\frac{d}{dt}\int_{t}^{b}\left(\log\frac{s}{t}\right)^{-\alpha}f(s)\frac{ds}{s}\right)$$

$$= \frac{-ab}{t\Gamma(1-\alpha)} \frac{d}{d\left(\frac{ab}{t}\right)} \int_{\frac{ab}{t}}^{b} \left(\log\frac{st}{ab}\right)^{-\alpha} f(s)\frac{ds}{s}$$
$$= \frac{-ab}{t\Gamma(1-\alpha)} \frac{-t^2}{ab} \frac{d}{dt} \int_{\frac{ab}{t}}^{b} \left(\log\frac{st}{ab}\right)^{-\alpha} f(s)\frac{ds}{s}$$
$$= \frac{t}{\Gamma(1-\alpha)} \frac{d}{dt} \int_{\frac{ab}{t}}^{b} \left(\log\frac{st}{ab}\right)^{-\alpha} f(s)\frac{ds}{s}.$$

Hence, ${}^{H}_{a}D^{\alpha}_{t}Qf(t) = Q^{H}_{t}D^{\alpha}_{b}f(t)$. Based on these, (ii) and (iii) can be proved similarly.

Lemma 2.9. [34] Suppose that X, Y, Z are reflexive Hilbert spaces, $f \in L(X, Z)$ and $g \in L(Y, Z)$. Then

$$Im(f) \subseteq Im(g)$$

is equivalent to

$$\exists K > 0, \ s.t. \parallel f^* z \parallel_{X^*} \leq K \parallel g^* z \parallel_{Y^*}, \ \forall z \in Z.$$

Lemma 2.10. [25] Let U be a closed, convex subset of a Hilbert space H. Assume that for $v \in U$, the functional $v \to J(v)$ is strict convex, differentiable and satisfies $J(v) \to +\infty$ as $||v|| \to +\infty$. Then the unique element u in U satisfying $J(u) = \inf_{v \in U} J(v)$ is characterized by

$$J'(u)(v-u) \ge 0, \quad \forall v \in U.$$

3. Main results. By Proposition 3.1 in [12], since system (1) is a linear system, without loss of generality, we can suppose $z_0(x) = 0$. Then, the solution of system (1) reduces to

$$z(x,t) = \int_{a}^{t} \left(\log\frac{t}{s}\right)^{\alpha-1} K_{\alpha}\left(\log\frac{t}{s}\right) Bu(s)\frac{ds}{s}.$$
 (11)

Define the operator $H: L^2([a,b], \mathbb{R}^m) \to L^2(\Omega)$,

$$Hu \triangleq \int_{a}^{b} \left(\log \frac{b}{s}\right)^{\alpha-1} K_{\alpha} \left(\log \frac{b}{s}\right) Bu(s) \frac{ds}{s}$$
$$= \int_{0}^{\log \frac{b}{\alpha}} s^{\alpha-1} K_{\alpha}(s) Bu(be^{-s}) ds$$
(12)

for any $u(t) \in L^2([a, b], \mathbb{R}^m)$. Since B is bounded and linear, let H^* , be the adjoint operator of H, that is, $\langle Hu, v \rangle = \langle u, H^*v \rangle$ for any $v \in L^2(\Omega)$. For any $v \in L^2(\Omega)$, one has

$$\langle Hu, v \rangle = \left\langle \int_{a}^{b} \left(\log \frac{b}{s} \right)^{\alpha - 1} K_{\alpha} \left(\log \frac{b}{s} \right) Bu(s) \frac{ds}{s}, v \right\rangle$$
$$= \int_{a}^{b} \left\langle \left(\log \frac{b}{s} \right)^{\alpha - 1} K_{\alpha} \left(\log \frac{b}{s} \right) \frac{Bu(s)}{s}, v \right\rangle ds$$
$$= \int_{a}^{b} \left\langle u(s), \left(\log \frac{b}{s} \right)^{\alpha - 1} K_{\alpha}^{*} \left(\log \frac{b}{s} \right) \frac{B^{*}v}{s} \right\rangle ds.$$

Hence,

$$H^*v = \frac{1}{t}B^*\left(\log\frac{b}{t}\right)^{\alpha-1}K^*_{\alpha}\left(\log\frac{b}{t}\right)v, \ \forall v \in L^2(\Omega).$$
(13)

 $\overline{7}$

In addition, the adjoint operator of the restriction map p_{ω} is defined by

$$p_{\omega}^{*}f(x) = \begin{cases} f(x), & x \in \omega, \\ 0, & x \in \Omega \setminus \omega. \end{cases}$$
(14)

When n = 1, we denote p_{ω} as $p_{1,\omega}$, so does $p_{1,\omega}^*$.

We can deduce the following results.

Theorem 3.1. The following statements are equivalent: (i) System (1) is regionally gradient exactly controllable on ω at time b; (ii) $Im (p_{\omega} \nabla H) = (L^2(\omega))^n$; (iii) $Ker (p_{\omega}) + Im (\nabla H) = (L^2(\Omega))^n$; (iv) There exists K > 0, such that $\forall z \in (L^2(\omega))^n$, $\| z \|_{(L^2(\omega))^n} \leq K \| H^* \nabla^* p_{\omega}^* z \|_{L^2(a,b;R^m)}$.

Proof. The equivalence between (i) and (ii) can be easily obtained from Definition 2.3. In Lemma 2.9, choose $X = Z = (L^2(\omega))^n$, $Y = (L^2(\Omega))^n$, f = I, the identity operator and $g = p_\omega \nabla H$, we have $(i) \Leftrightarrow (iv)$. So we only need to prove $(ii) \Leftrightarrow (iii)$.

 $(ii) \Rightarrow (iii): \forall x_1 \in Ker(p_{\omega}), x_2 \in Im(\nabla H), \text{ since }$

$$p_{\omega}\left(x_{1}+x_{2}\right)=p_{\omega}x_{2}\in Im\left(p_{\omega}\nabla H\right)=\left(L^{2}(\omega)\right)^{n},$$

it follows that $x_1 + x_2 \in (L^2(\Omega))^n$, that is,

$$Ker(p_{\omega}) + Im(\nabla H) \subseteq \left(L^{2}(\Omega)\right)^{n}.$$
(15)

Next, $\forall x \in (L^2(\Omega))^n$, define $\widetilde{x} \triangleq p_\omega x \in (L^2(\omega))^n = Im(p_\omega \nabla H)$, and $y \triangleq x - \widetilde{x}$. So, there exists a $u \in L^2(\Omega)$, such that $p_\omega \nabla H u = \widetilde{x}$. Then $\widetilde{x} \in Im(\nabla H)$. Besides,

$$p_{\omega}y = p_{\omega}\left(x - \widetilde{x}\right) = p_{\omega}x - p_{\omega}\widetilde{x} = 0$$

that is, $y \in Ker(p_{\omega})$. Hence,

$$\left(L^2(\Omega)\right)^n \subseteq Ker\left(p_{\omega}\right) + Im(\nabla H).$$
(16)

 $(iii) \Rightarrow (ii)$: From (iii), for any $x \in (L^2(\omega))^n \subseteq (L^2(\Omega))^n$, there exists $x_1 \in Ker(p_\omega)$ and $x_2 \in Im(\nabla H)$ such that $x = x_1 + x_2$. Then a $u \in L^2(\Omega)$ can be found satisfying $\nabla Hu = x_2$. Hence,

$$x = p_{\omega}x = p_{\omega}\left(x_1 + \nabla Hu\right) = p_{\omega}\nabla Hu \in Im\left(p_{\omega}\nabla H\right)$$

that is,

$$\left(L^2(\Omega)\right)^n \subseteq Im\left(p_\omega \nabla H\right). \tag{17}$$

Next, $\forall x \in Im (p_{\omega} \nabla H)$, together with the definition of H, we immediately get that there exists a $u \in L^2(\Omega)$, such that $p_{\omega} \nabla H u = x \in (L^2(\omega))^n$, namely

$$Im\left(p_{\omega}\nabla H\right)\subseteq\left(L^{2}(\omega)\right)^{n}.$$
(18)

Combining $(15) \sim (18)$, we get that $(ii) \Leftrightarrow (iii)$ and complete the proof.

Theorem 3.2. The following statements are equivalent:

(i) System (1) is regionally gradient approximately controllable on ω at time b;

(*ii*) $\overline{Im(p_{\omega}\nabla H)} = (L^2(\omega))^n$;

(*iii*) $Ker(p_{\omega}) + \overline{Im(\nabla H)} = (L^2(\Omega))^n;$

(iv) $p_{\omega} \nabla H H^* \nabla^* p_{\omega}^*$ is a positive definite operator;

(v) If $\langle p_{\omega} \nabla Hu, z \rangle = 0$, $\forall u \in L^{2}(\Omega)$, leads to z = 0, where $\langle \cdot, \cdot \rangle$ denotes the inner product.

Proof. Similar to Theorem 3.1, one has $(i) \Leftrightarrow (ii) \Leftrightarrow (iii)$. Then we prove $(ii) \Leftrightarrow (iv)$ and $(ii) \Leftrightarrow (v)$.

 $(ii) \Leftrightarrow (iv)$: For any $y, z \in (L^2(\omega))^n$,

$$\langle p_{\omega} \nabla H H^* \nabla^* p_{\omega}^* y, \, z \rangle = \langle y, \, p_{\omega} \nabla H H^* \nabla^* p_{\omega}^* z \rangle$$

and $\langle p_{\omega} \nabla H H^* \nabla^* p_{\omega}^* y, y \rangle = \langle H^* \nabla^* p_{\omega}^* y, H^* \nabla^* p_{\omega}^* y \rangle$. These, together with the equivalence between $\overline{Im} (p_{\omega} \nabla H) = (L^2(\omega))^n$ and the domain of $p_{\omega} \nabla H H^* \nabla^* p_{\omega}^*$ is dense in $(L^2(\omega))^n$, lead to the result.

 $(ii) \Leftrightarrow (v)$: We can easily see that $(ii) \Rightarrow (v)$ and $\overline{Im(p_{\omega}\nabla H)} \subseteq (L^2(\omega))^n$. Moreover, we claim that $(L^2(\omega))^n \subseteq \overline{Im(p_{\omega}\nabla H)}$. If not, there is a nonzero $z \in (L^2(\omega))^n \setminus \overline{Im(p_{\omega}\nabla H)}$, such that

$$\langle p_{\omega} \nabla Hu, z \rangle = 0, \ \forall u \in L^2(\Omega),$$

which leads to a contradiction.

Next, we will take research on the description of the actuators and give the minimum number of the actuators to guarantee the desired performance. By [17], we see that an actuator can be characterized by (P, d), where $P \subseteq \Omega$ represents the working area of the actuator and d is its spatial distribution. Here, we suppose that the system is controlled by m actuators with corresponding characteristics $(P_i, d_i(x))$, where $d_i(x) \in L^2(\Omega)$, i = 1, 2, ..., m. Let

$$Bu = \sum_{i=1}^{m} \chi_{P_i} d_i(x) u_i(t),$$
(19)

where $u = (u_1, \ldots, u_m)$, $u_i \in L^2([a, b], \mathbb{R})$ and χ_{P_i} denotes the indicator function on P_i . Then, system (1) is equivalent to

$$\begin{cases} {}^{HC}_{a} D^{\alpha}_{t} z(x,t) = A z(x,t) + \sum_{i=1}^{m} \chi_{P_{i}} d_{i}(x) u_{i}(t), \\ z(x,a) = 0 \text{ in } \Omega, \\ z(\xi,t) = 0 \text{ on } \partial\Omega \times [a,b], \end{cases}$$

$$(20)$$

whose solution is given by

$$z(x,t) = \int_{a}^{t} \left(\log \frac{t}{s}\right)^{\alpha-1} K_{\alpha} \left(\log \frac{t}{a}\right) \sum_{i=1}^{m} \chi_{P_{i}} d_{i}(x) u_{i}(s) \frac{ds}{s}$$
$$= \int_{0}^{\log \frac{t}{a}} s^{\alpha-1} K_{\alpha}(s) \chi_{P_{i}} d_{i}(x) u_{i}(te^{-s}) ds.$$
$$(21)$$

Suppose that $\lambda_1, \ldots, \lambda_k, \ldots$ are the eigenvalues of -A with corresponding multiplicities r_1, \ldots, r_k, \ldots , satisfying $0 < \lambda_1 < \ldots < \lambda_k < \ldots$, and $\lim_{k\to\infty} \lambda_k = \infty$. The orthonormal eigenfunctions $\alpha_{kj}(x)$, $j = 1, \ldots, r_k$ corresponding to λ_k , for $k = 1, 2, \ldots$ consist of an orthonormal basis of $L^2(\Omega)$. With this, for any $z \in L^2(\Omega)$, the C_0 -semigroup $\{T(t)\}_{t\geq 0}$ can be shown as

$$T(t)z = \sum_{k=1}^{\infty} \sum_{j=1}^{r_k} e^{-\lambda_j t} \langle z, \, \alpha_{kj}(x) \rangle \alpha_{kj}(x),$$

that is

$$z = \sum_{k=1}^{\infty} \sum_{j=1}^{r_k} \langle z, \alpha_{kj}(x) \rangle \alpha_{kj}(x).$$
(22)

From (22), the solution of system (1) in (21) can be expressed by

$$z(x,t) = \sum_{k=1}^{\infty} \sum_{j=1}^{r_k} \sum_{i=1}^m \int_0^{\log \frac{t}{a}} s^{\alpha-1} E_{\alpha,\,\alpha} \left(-\lambda_k s^{\alpha}\right) d_{kj}^i(x) u_i\left(te^{-s}\right) ds \cdot \alpha_{kj}(x), \quad (23)$$

where $d_{kj}^i(x) \triangleq \langle \chi_{P_i} d_i(x), \alpha_{kj}(x) \rangle.$

Theorem 3.3. Define

$$D_k^l \triangleq \frac{\partial}{\partial x_l} \begin{bmatrix} d_{k1}^1(x)\alpha_{k1}(x) & \cdots & d_{kr_k}^1(x)\alpha_{kr_k}(x) \\ \vdots & \cdots & \vdots \\ d_{k1}^m(x)\alpha_{k1}(x) & \cdots & d_{kr_k}^m(x)\alpha_{kr_k}(x) \end{bmatrix}.$$

Then $(P_i, d_i(x))$, i = 1, ..., m are gradient ω -strategic if and only if for any $z \in (L^2(\omega))^n$,

$$\sum_{k=1}^{\infty} \sum_{j=1}^{r_k} t^{\alpha-1} E_{\alpha,\,\alpha} \left(-\lambda_k t^{\alpha} \right) \sum_{l=1}^n D_k^l \Phi_{kl} = 0 \; \Rightarrow \; z = 0, \tag{24}$$

where $z = (z_1, \ldots, z_n)^{\top}$, $\Phi_{kl} \triangleq (z_{k1l}, \ldots, z_{kr_kl})^{\top}$ and $z_{kjl} \triangleq \langle p_{1,\omega}^* z_l, \alpha_{kj}(x) \rangle$. When n = 1, (24) is equivalent to

$$m \ge r \triangleq \sup \{r_k\} \text{ and } \operatorname{rank} D_k^1 = r_k,$$

for k = 1, 2, ...

Proof. According to Definition 2.4 and Theorem 3.2, we know $(P_i, d_i(x)), i = 1, \ldots, m$ are gradient ω -strategic is equivalent to z = 0, provided that $\langle p_\omega \nabla Hu, z \rangle = 0$, for any $u \in L^2([a, b], \mathbb{R}^m)$.

From $\langle p_{\omega} \nabla H u, z \rangle = 0$ and (23), we have

$$\sum_{l=1}^{n} \langle \sum_{k=1}^{\infty} \sum_{j=1}^{r_k} \sum_{i=1}^{m} \int_{0}^{\log \frac{b}{a}} s^{\alpha-1} E_{\alpha, \alpha} \left(-\lambda_k s^{\alpha} \right) \times u_i \left(b e^{-s} \right) ds \cdot \frac{\partial}{\partial x_l} \left(d_{kj}^i(x) \alpha_{kj}(x) \right), \, p_{1\omega}^* z_l \rangle = 0.$$

$$(25)$$

Then, the arbitrariness of u leads to the equivalence between (25) and

$$\sum_{k=1}^{\infty} \sum_{j=1}^{r_k} t^{\alpha-1} E_{\alpha,\alpha} \left(-\lambda_k t^{\alpha} \right) \sum_{l=1}^n D_k^l \Phi_{kl} = 0$$

and the proof of the first part is completed.

When n = 1, since $t^{\alpha-1}E_{\alpha,\alpha}(-\lambda_k t^{\alpha}) > 0$, for any $t \in [a, b]$, the equivalence between (24) and

 $m \ge \sup \{r_k\}$ and rank $D_k^1 = r_k, \quad k = 1, 2, \dots,$

can be easily derived by the knowledge of linear algebra.

Remark 3. If for every k, λ_k is a single eigenvalue of -A, Theorem 3.3 shows that we can steer system (1) to be regionally gradient approximately controllable by one actuator; and if there is a \tilde{k} , such that the multiplicity of $\lambda_{\tilde{k}}$ is infinite, then the number of actuators must be infinite.

The last part in this section aims to provide a method to find out the optimal actuators with minimum energy to achieve the regional gradient approximate controllability among all admissible ones. The HUM, which was first introduced by Lions [25, 26], is the main method to be used.

For any given target state $f \in (L^2(\omega))^n$, define

$$U_{ad} \triangleq \left\{ u \in L^2(\Omega) \mid p_\omega \nabla H u = f(x) \right\},\tag{26}$$

and the minimum energy (cost) functional

$$\inf_{u \in U_{ad}} J(u) \triangleq \inf_{u \in U_{ad}} \int_{a}^{b} \| u(t) \|_{\mathbb{R}^{m}}^{2} dt.$$
(27)

When system (1) is regionally gradient controllable, we can easily see that U_{ad} is nonempty.

It's also worth mentioning that the cost for regional gradient controllability is not more than that for regional controllability. Let \tilde{U}_{ad} be the admissible control set for the corresponding regional controllability. Since Hu = f(x) implies $\nabla Hu = \nabla f(x)$, thus $\tilde{U}_{ad} \subseteq U_{ad}$ and

$$\inf_{u \in U_{ad}} J(u) \le \inf_{u \in \widetilde{U}_{ad}} J(u).$$

Next, by using the HUM, we'll provide the unique solution to the minimum energy functional (27) to guarantee the regional gradient approximate controllability.

Define $G \triangleq \{g \in (L^2(\Omega))^n \mid g = 0 \text{ in } \Omega \setminus \omega \text{ and } \exists ! \tilde{g} \in H^1_0(\Omega), s.t. \nabla \tilde{g} = g\}.$ Then, $\tilde{g} = \nabla^* p^*_{\omega} g \in H^1_0(\Omega)$, for any $g \in G$. Consider

$$\begin{cases} Q_t^H D_b^{\alpha} \varphi(x,t) = A^* Q \varphi(x,t) \text{ in } \Upsilon, \\ \lim_{t \to b} Q_t^H D_b^{\alpha-1} \varphi(x,t) = \nabla^* p_{\omega}^* g(x) \text{ in } \Omega, \\ \varphi(\xi, b-t) = 0 \text{ on } \partial\Omega \times [a,b]. \end{cases}$$
(28)

According to Lemma 2.8 and then utilizing Lemma 2.6, the unique solution of system (28) satisfies:

$$\varphi(x,t) = \left(\log\frac{b}{t}\right)^{\alpha-1} K^*_{\alpha}\left(\log\frac{b}{t}\right) \nabla^* p^*_{\omega} g(x).$$
(29)

Define

$$\|g\|_{G}^{2} \triangleq \int_{a}^{b} \left\|\frac{1}{t}B^{*}K(t)\nabla^{*}p_{\omega}^{*}g(x)\right\|^{2} dt, \qquad (30)$$

where $K(t) = \left(\log \frac{b}{t}\right)^{\alpha-1} K_{\alpha}^* \left(\log \frac{b}{t}\right)$, then we have the following lemma.

Lemma 3.4. If system (1) is regionally gradient approximately controllable, then (30) is a norm on G.

Proof. It's obvious that (30) defines a semi-norm on G.

From $||g||_G = 0$, we have

$$\frac{1}{t}B^*K(t)\nabla^*p^*_{\omega}g(x) = 0.$$

If system (1) is regionally gradient approximately controllable, from Theorem 3.2, we know $\overline{Im(p_{\omega}\nabla H)} = (L^2(\omega))^n$. Hence,

$$Ker\left(H^*\nabla^* p_\omega^*\right) = \{0\},\$$

that is, $||g||_G = 0$ leads to g = 0. Thus, (30) defines a norm on G.

Now, consider the following two systems

$$\begin{pmatrix}
^{HC} B^{\alpha} D^{\alpha}_{t} \Psi_{1}(x,t) = A \Psi_{1}(x,t) + \frac{1}{t} B B^{*} \varphi(x,t) \text{ in } \Upsilon, \\
^{\Psi_{1}}(x,a) = 0 \text{ in } \Omega, \\
^{\Psi_{1}}(\xi,t) = 0 \text{ on } \partial\Omega \times [a,b]
\end{cases}$$
(31)

and

$$\begin{cases} {}^{HC}_{a} D_{t}^{\alpha} \Psi_{2}(x,t) = A \Psi_{2}(x,t) \text{ in } \Upsilon, \\ \Psi_{2}(a) = y_{0}(x) \text{ in } \Omega, \\ \Psi_{2}(\xi,t) = 0 \text{ on } \partial\Omega \times [a,b]. \end{cases}$$
(32)

Define $Fg \triangleq p_{\omega} \nabla \Psi_1(x, b)$. According to the superposition principle in linear system, we can provide the regional gradient approximate controllability of system (1) if we can solve

$$Fg = f(x) - p_{\omega} \nabla \Psi_2(x, b). \tag{33}$$

Theorem 3.5. If system (1) is regionally gradient approximately controllable, then for any given $f(x) \in (L^2(\omega))^n$, (33) exists a unique solution $g \in G$, and the actuator $u^*(t) = \frac{1}{t}B^*\varphi(x,t)$ is the unique solution of (27).

Proof. Given any $g \in G$, it yields that

$$\begin{split} \langle g, Fg \rangle &= \langle g, p_{\omega} \nabla \Psi_{1}(x, b) \rangle = \langle \nabla^{*} p_{\omega}^{*} g, \Psi_{1}(x, b) \rangle \\ &= \langle \nabla^{*} p_{\omega}^{*} g, \int_{a}^{b} \left(\log \frac{b}{s} \right)^{\alpha - 1} K_{\alpha} \left(\log \frac{b}{s} \right) BB^{*} \varphi(x, s) \frac{ds}{s^{2}} \rangle \\ &= \int_{a}^{b} \left\| \frac{1}{t} B^{*} \varphi(x, t) \right\|^{2} dt = \|g\|_{G}^{2} \,. \end{split}$$

Hence, (33) exists a unique solution \widehat{g} . From $u^*(t) = \frac{1}{t}B^*\varphi(x,t)$, we can easily check that $p_{\omega}\nabla Hu^* = f(x)$, that is, $u^* \in U_{ad}$.

For any $\widetilde{u} \in L^2(\Omega)$, satisfying $p_{\omega} \nabla H \widetilde{u} = f(x)$, we have $p_{\omega} \nabla H u^* = p_{\omega} \nabla H \widetilde{u}$. Therefore, it leads to

$$J'(u^*) (u^* - \widetilde{u}) = 2 \int_a^b \langle u^*(s), u^*(s) - \widetilde{u}(s) \rangle ds$$
$$= 2 \int_a^b \left\langle \frac{1}{s} B^* \varphi(x, s), u^*(s) - \widetilde{u}(s) \right\rangle ds$$
$$= 2 \left\langle \nabla^* p^*_{\omega} g, \int_a^b T(s) \frac{ds}{s} \right\rangle$$
$$= 2 \langle g, p_{\omega} \nabla H u^* - p_{\omega} \nabla H \widetilde{u} \rangle = 0,$$

where

$$T(s) = \left(\log \frac{b}{s}\right)^{\alpha - 1} K_{\alpha} \left(\log \frac{b}{s}\right) B\left(u^*(s) - \widetilde{u}(s)\right).$$

By applying Lemma 2.10, we conclude that u^* is the unique solution of (27).

Remark 4. If we choose f(x) = 0 in Definition 2.3, then the regional gradient exact/approximate null controllability can be guaranteed.

4. An example. Let $\Omega = [-1,1] \times [-1,1]$ and consider the following diffusion system with one zone actuator:

$$\begin{cases} {}^{HC}_{2}D^{0.5}_{t}z(x,t) = -\Delta z(x,t) + \chi_{P}u(t) \text{ in } \Upsilon,\\ z(x,2) = 0, \text{ in } \Omega,\\ z(x,t) = 0, \text{ on } \partial\Omega \times [2,4], \end{cases}$$
(34)

where $\widetilde{\Upsilon} = \Omega \times [2,4]$, $x = (x_1, x_2)^{\top}$ and $\Delta = \frac{\partial^2}{\partial x_1^2} + \frac{\partial^2}{\partial x_2^2}$, the two dimensions Laplace operator. Here, $A = -\Delta$ generates a C_0 -semigroup $\{T(t)\}$ on $L^2(\Omega)$ and $-A = \Delta$ is a uniformly elliptic operator. As we know, the eigenvalue λ_{kl} and the corresponding eigenfunction $\alpha_{kl}(x)$ of A are $\lambda_{kl} = (k^2 + l^2) \pi^2$ and $\alpha_{kl}(x) = 2 \sin(k\pi x_1) \sin(l\pi x_2)$, respectively, for $k, l = 1, 2, \ldots$ and $x \in \Omega$.

According to (13), for any $z \in L^2(\Omega)$, it follows that

$$H^* \nabla^* z = \frac{1}{t} N(t) \sum_{k,l=1}^{\infty} E_{0.5,\,0.5} \left(\lambda_{kl} N(t) \right) \left\langle \nabla^* z, \, \alpha_{kl}(x) \right\rangle M_{kl}$$

where $N(t) = \left(\log \frac{4}{t}\right)^{-0.5}$ and $M_{kl} = \int_P \alpha_{kl}(x) dx$. When we consider the gradient approximate controllability on the whole region at time 4, that is, $P = \Omega$, then

$$M_{kl} = \int_{-1}^{1} \int_{-1}^{1} 2\sin(k\pi x_1)\sin(l\pi x_2)dx_1dx_2 \equiv 0.$$

Hence, we have

$$H^* \nabla^* z \equiv 0, \quad \forall z \in L^2(\Omega),$$
(35)

which implies that $Ker(H^*\nabla^*) \neq \{0\}$, i.e., $\overline{Im(\nabla H)} \neq L^2(\Omega)$. From Theorem 3.2, we conclude that system (34) is not gradient approximately controllable on the whole interested domain at time 4.

Next, we show that system (34) is regionally gradient approximately controllable on a subinterval $\omega \subsetneq \Omega$.

Let $\omega = [0,1] \times [0,1]$ and $z = \sin(p\pi x_1) \cos(q\pi x_2)$ with even numbers p,q. Then

$$H^* \nabla^* p_{\omega}^* z = \frac{1}{t} N(t) \sum_{k,l} E_{0.5,\,0.5} \left(-\left(k^2 + l^2\right) \pi^2 N(t) \right) J_{klpq} \neq 0,$$

where

$$J_{klpq} = \frac{8p}{kl\pi} \left(\frac{1}{(k+p)\pi} - \frac{1}{(k-p)\pi} \right) \left(\frac{1}{(l+q)\pi} - \frac{1}{(l-q)\pi} \right),$$

for odd numbers k, l.

Hence, $z = \sin(p\pi x_1) \cos(q\pi x_2)$ is reachable and thus regionally gradient approximately controllable on ω at time 4. Since the eigenvalues of A are all of multiplicity 1, that is, $r_k = 1$ for all k, then r = 1 and $rankD_k^1 = rankD_k^2 = 1$. Hence, from Theorem 3.3, the zone actuator is gradient ω -stratigic, which coincides with Remark 3. Moreover, the regional gradient approximate controllability of system (34) on ω at time 4 shows that (30) defines a norm on G according to Lemma 3.4. It follows from $\langle Bu, \varphi(x, t) \rangle = \langle u, B^* \varphi(x, t) \rangle$ and $Bu = \chi_{\omega} u(t)$ that

$$B^*\varphi(x,t) = \int_{L^2(\omega)} \varphi(x,t) dx.$$

Therefore, according to Theorem 3.5, the unique minimum energy control can be presented by

$$u^*(t) = \frac{1}{t} \int_{L^2(\omega)} \varphi(x, t) dx.$$

5. **Conclusion.** In this paper, we established some effective necessary and sufficient conditions on the regional gradient controllability of Hadamard-Caputo time fractional diffusion systems. The characteristics of admissible actuators and the optimal control described by the minimum energy functional were also derived. Finally, the illustrative example showed the application of our results in practical models.

6. Further works. [28] considered a rather stronger notion of null controllability, which requires the state of system stays at rest after the final moment. In this sense, a fractional system is not null controllable. It's natural to ask whether it is controllable in other sense, such as regionally gradient approximately controllable. Similar to the definition of null controllability in [28], one should take into account the memory effect of the fractional derivative for the regional gradient approximate controllability. This is beyond the scope of this paper and will be analyzed in detail in another paper.

Acknowledgments. We would like to thank the referees for all the comments and suggestions that made possible a better version of this paper.

REFERENCES

- A. Aacute and D. Castillo-Negrete, Fluid limit of the continuous-time random walk with general Levy jump distribution functions, *Physical Review E Statistical Nonlinear and Soft Matter Physics*, **76** (2007), 041105.
- [2] S. Abbas, M. Benchohra, J. E. Lazreg and Y. Zhou, A survey on Hadamard and Hilfer fractional differential equations: Analysis and stability, *Chaos Solitons and Fractals*, **102** (2017), 47–71.
- [3] L. Afifi, A. El Jai and E. Zerrik, *Regional Analysis of Linear Distributed Parameter Systems*, Princeton University Press, Princeton, 2005.
- [4] B. Ahmad, S. K. Ntouyas and J. Tariboon, et al., *Hadamard-Type Fractional Differential Equations, Inclusions and Inequalities*, Springer International Publishing, 2017.
- [5] P. L. Butzer, A. A. Kilbas and J. J. Trujillo, Compositions of Hadamard-type fractional integration operators and the semigroup Journal of Mathematical Analysis and Applications, 269 (2002), 387–400.
- [6] L. C. Evans, Partial Differential Equations, Vol. 19, American Mathematical Society, 2010.
- [7] R. Garra and F. Polito, On some operators involving Hadamard derivatives, Integral Transforms and Special Functions, 24 (2013), 773–782.
- [8] F. Ge, Y. Q. Chen and C. Kou, *Regional Analysis of Time-Fractional Diffusion Processes*, Springer, 2018.
- [9] F. Ge, Y. Q. Chen and C. Kou, Regional gradient controllability of sub-diffusion processes, Journal of Mathematical Analysis and Applications, 440 (2016), 865–884.
- [10] F. Ge, Y. Q. Chen, C. Kou and I. Podlubny, On the regional controllability of the sub-diffusion process with Caputo fractional of Fractional Calculus and Applied Analysis, 19 (2016), 1262–1281.
- [11] F. Ge, Y. Q. Chen and C. Kou, Regional controllability analysis of fractional diffusion equations with Riemann-Liouville time fr Automatica, 76 (2017), 193–199.
- [12] F. Ge, Y. Q. Chen and C. Kou, Actuator characterisations to achieve approximate controllability for a class of fractional sub-dif International Journal of Control, 90 (2017), 1212–1220.
- [13] Z. Gong, D. Qian and C. Li, et al., On the Hadamard type fractional differential system, Fractional Dynamics and Control. Springer, New York, (2012), 159–171.
- [14] V. Govindaraj and R. K. George, Controllability of fractional dynamical systems—A functional analytic approach, Mathematical Control and Related Fields, 7 (2017), 537–562.

REGIONAL GRADIENT CONTROLLABILITY OF ULTRA-SLOW DIFFUSIONS ... 15

- [15] J. R. Graef, S. R. Grace and E. Tunc, Asymptotic behavior of solutions of nonlinear fractional differential equations with Caput Fractional Calculus and Applied Analysis, 20 (2017), 71–87.
- [16] J. Hadamard, Essai sur letude des fonctions donnees par leur developpement de Taylor, Journal de Mathematiques Pures et Appliquees, 8 (1892), 101–186 (In French).
- [17] A. EI Jai and A. J. Pritchard, Sensors and Controls in the Analysis of Distributed Systems, Halsted Press, 1988.
- [18] F. Jarad, T. Abdeljawad and D. Baleanu, Caputo-type modification of the Hadamard fractional derivatives, Advances in Difference Equations, 2012 (2012), 1–8.
- [19] Q. Katatbeha and A. Al-Omarib, Existence and uniqueness of mild and classical solutions to fractional order Hadamard-type O Journal of Nonlinear Science and Applications, 9 (2016), 827–835.
- [20] F. A. Khodja, F. Chouly and M. Duprez, Partial null controllability of parabolic linear systems, Mathematical Control and Related Fields, 6 (2016), 185–216.
- [21] F. A. Khodja, A. Benabdallah, M. G. Burgos and L. Teresa, Recent results on the controllability of linear coupled parabolic problems—A survey, *Mathematical Control and Related Fields*, 1 (2011), 267–306.
- [22] A. A. Kilbas, H. M. Srivastava and J. J. Trujillo, Theory and Applications of Fractional Differential Equations, Elsevier, 2006.
- [23] A. A. Kilbas, Hadamard-type fractional calculus, Journal of the Korean Mathematical Society, 38 (2001), 1191–1204.
- [24] H. Leiva, N. Merentes and J. L. Sanchez Approximate controllability of semilinear reaction diffusion equations, Mathematical Control and Related Fields, 2 (2012), 171–182.
- [25] J. L. Lions, Optimal Control of Systems Governed by Partial Differential Equations, Vol. 170, Springer Verlag, 1971.
- [26] J. L. Lions, Exact controllability, stabilization and perturbations for distributed systems, SIAM Review, 30 (1988), 1–68.
- [27] Y. Liu, Survey and new results on boundary-value problems of singular fractional differential equations with impulse effects, *Electronic Journal of Differential Equations*, **296** (2016), 1– 177.
- [28] Q. Lü and E. Zuazua, On the lack of controllability of fractional in time ODE and PDE, Mathematics of Control Signals and Systems, 28 (2016), Art. 10, 21 pp.
- [29] F. Mainardi, P. Paradisi and R. Gorenflo, Probability distributions generated by fractional diffusion equations, *Physics*, (2007), 312–350.
- [30] F. Mainardi, A. Mura and G. Pagnini, et al., Sub-diffusion equations of fractional order and their fundamental solutions, *Mathematical Methods in Engineering*. Springer, (2007), 23–55.
- [31] T. Mur and H. R. Henriquez, Relative controllability of linear systems of fractional order with delay, Mathematical Control and Related Fields, 5 (2015), 845–858.
- [32] I. Podlubny, Fractional Differential Equations, Academic Press, 1999.
- [33] Y. Povstenko, Fractional Thermoelasticity, Springer International Publishing, 2015.
- [34] A. J. Pritchard and A. Wirth, Unbounded control and observation systems and their duality, SIAM Journal on Control and Optimization, 16 (1978), 535–545.
- [35] S. G. Samko, A. A. Kilbas and O. I. Marichev, Integrals and Derivatives of Fractional Order and Some of Their Applications, Gordon and Breach Science Publishers, Yverdon, 1993.
- [36] J. Tariboon, S. K. Ntouyas and C. Thaiprayoon, Nonlinear Langevin equation of Hadamard-Caputo type fractional derivatives Advances in Mathematical Physics, 2014 (2014), Art. ID 372749, 15 pp.
- [37] G. M. Zaslavsky, Chaos, fractional kinetics, and anomalous transport, *Physics Reports*, 371 (2002), 461–580.
- [38] C. Zeng and Y. Q. Chen, Optimal random search, fractional dynamics and fractional calculus, Fractional Calculus and Applied Analysis, 17 (2014), 321–332.
- [39] E. Zerrik, A. Boutoulout and A. Kamal, Regional gradient controllability of parabolic systems, International Journal of Applied Mathematics and Computer Science, 9 (1999), 767–787.
- [40] E. Zerrik, A. Kamal and A. Boutoulout, Regional gradient controllability and actuators, International Journal of Systems Science, 33 (2002), 239–246.
- [41] E. Zerrik and F. Ghafrani, Regional gradient-constrained control problem. Approaches and simulations, Journal of Dynamical and Control Systems, 9 (2003), 585–599.
- [42] Y. Zhou and F. Jiao, Existence of mild solutions for fractional neutral evolution equations, Computers and Mathematics with Applications, 59 (2010), 1063–1077.

Received July 2018; revised February 2019.

RUIYANG CAI, FUDONG GE, YANGQUAN CHEN AND CHUNHAI KOU

E-mail address: 2151359@mail.dhu.edu.cn E-mail address: gefd@cug.edu.cn E-mail address: ychen53@ucmerced.edu E-mail address: kouchunhai@dhu.edu.cn